

UCD9112 Device Errata

The UCD9112 device has the following anomalies.

Errata Index

1. The WRITE_PROTECT command does not prevent writing to other PMBus commands as per the specification.
2. VOUT_MAX warning bit in STATUS_VOUT register is not set.
3. Soft start (or stop) timing might get affected during faults.
4. System does not do proper number of retries for fault response of continue operation for 0 ms.
5. System startup issues when VIN_OFF limit is higher than VIN_ON limit.
6. Address 12 should not be assigned as PMBus address.
7. The PMBus GROUP command is not supported.

Erratum # 1

The WRITE_PROTECT command does not prevent writing to other PMBus commands, as per the specification.

Detailed Description of Issue

When the WRITE_PROTECT command has a non-zero value, it does not properly prevent writing to all PMBus commands (excluding WRITE_PROTECT, OPERATION, ON_OFF_CONFIG, and VOUT_COMMAND PMBus commands) that it should. This allows a PMBus master to write to these other commands, even when WRITE_PROTECT value is not equal to 0.

Suggested workarounds

The Configuration Security feature will allow protection of all commands on a command by command basis. For more information see the application report *Configuration Security for UCD91xx Digital Controllers* ([SLUA428](#)).

Erratum # 2

VOUT_MAX warning bit in STATUS_VOUT register is not set.

Detailed Description of Issue

When the Vout set point is configured to be greater than VOUT_MAX value, the appropriate bit in the STATUS_VOUT register is not set.

Suggested workarounds

Do not set Vout set point (or VOUT_COMMAND) greater than the allowed voltage in VOUT_MAX register and expect the status bit to be asserted.

Erratum # 3

Soft start (or stop) timings might get affected during faults.

Detailed Description of Issue

During a fault, the system might not achieve proper soft-start or soft-stop timing if a fault happens during the ramp up or ramp down process. The timing of the ramp will typically be higher than configured.

Suggested workarounds

No workaround as of now.

Erratum # 4

Erratum # 4

System does not do proper number of retries for fault response of continue operation for 0 ms.

Detailed Description of Issue

When VOUT_OV_FAULT_RESPONSE is set to continue operation for 0 ms and a non-zero number of retries, the system will not attempt to retry the proper number of times. It is typically less than the configured number of retries.

Suggested workarounds

No workaround as of now.

Erratum # 5

System startup issues when VIN_OFF limit is higher than VIN_ON limit.

Detailed Description of Issue

The UCD9112 allows users to configure VIN_OFF limit higher than VIN_ON (VIN_OFF > VIN_ON). The PMBus peripheral will not NACK this transaction. If the system attempts to start up with this configuration set, the power supply will not operate properly until input voltage Vin is higher than VIN_OFF limit.

Suggested workarounds

This is a misconfiguration from a user side. The user needs to set the VIN_ON limit higher than the VIN_OFF limit.

Erratum # 6

Address 12 should not be assigned as PMBus address.

Detailed Description of Issue

When the UCD9112 is discovering its PMBus address by sampling ADDR0 and ADDR1 on startup, it incorrectly allows address 12 to be discovered. This is the SMBus Alert Response address and should not be used as a PMBus slave.

Suggested workarounds

To work around this issue, do not resistor-program ADDR0 and ADDR1 to allow an address of 12 to be assigned as a PMBus address for the device.

Erratum # 7

The PMBus GROUP command is not supported.

Detailed Description of Issue

The PMBus GROUP command is not supported.

Suggested workarounds

No workaround as of now.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DSP	dsp.ti.com
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
Low Power Wireless	www.ti.com/lpw

Applications

Audio	www.ti.com/audio
Automotive	www.ti.com/automotive
Broadband	www.ti.com/broadband
Digital Control	www.ti.com/digitalcontrol
Military	www.ti.com/military
Optical Networking	www.ti.com/opticalnetwork
Security	www.ti.com/security
Telephony	www.ti.com/telephony
Video & Imaging	www.ti.com/video
Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2007, Texas Instruments Incorporated