
Implementing Perpetual PoE and Fast PoE

Introduction

This application note describes how to implement Perpetual PoE (PPoE) and Fast PoE with Microchip's PD69210/PD69220 controller with the PD69208T4/PD69204T4/PD69208M Manager or PD39210 controller with the PD39208 Manager.

Perpetual PoE

PPoE supplies uninterrupted power to the connected Power Device (PD) even when the Power Sourcing Equipment (PSE) switch is rebooting.

Fast PoE

Fast PoE stores the last PoE power settings and switches on power when the AC power is plugged in (within a few seconds of switching on the power) without waiting for the host switch to boot up.

Table of Contents

Introduction.....	1
1. Hardware Support.....	3
1.1. Reset Pin.....	3
1.2. Disable Ports Pin.....	3
2. Software Support.....	4
2.1. Power-up and Reboot.....	4
2.2. Flash Memory.....	6
3. Schematics.....	7
4. Revision History.....	8
The Microchip Website.....	9
Product Change Notification Service.....	9
Customer Support.....	9
Microchip Devices Code Protection Feature.....	9
Legal Notice.....	10
Trademarks.....	10
Quality Management System.....	11
Worldwide Sales and Service.....	12

1. Hardware Support

This section describes the hardware requirements to support Ppoe and Fast PoE.

1.1 Reset Pin

The Reset pin of the controller must stay high during host reboot. This can be implemented by using a tri-state buffer output from the host and a pull-up resistor to 3.3 V on the controller xRESET pin. The xRESET is pin 26 on the PD69210 and PD39210 and pin 19 on the PD69220.

1.2 Disable Ports Pin


The Disable Ports pin of the controller must stay high during host reboot. This can be implemented by using a tri-state buffer output from the host and a pull-up resistor to 3.3 V on the controller xDISABLE_PORTS pin. xDISABLE_PORTS is pin 4 on PD69210 and PD39210 and pin 31 on PD69220.

If the xDISABLE_PORTS pin is not used, keep it pulled up to 3.3 V.

After the host controller finishes the reboot, it should not reset the PoE system or pull the above signals low.

To support Fast PoE, the above signals must be pulled high immediately after power-up to allow the PoE controller to initialize and start powering ports before the host controller finishes the reboot cycle.

Figure 1-1. Disable Ports Pin Setting—Schematic Diagram



2. Software Support

This section describes the host software requirements that must be implemented to support PPoE and Fast PoE.

2.1 Power-up and Reboot

The host must distinguish between power-up and reboot. To avoid momentary disconnect of PoE power to the ports, the host must not reconfigure the PoE system parameters if the system reset has not been completed.

The system reset can be achieved by using host indications or utilizing the Private Label field in the PD692x0 communication protocol to detect if the PoE system has experienced a Reset event.

Set the Private Label value by using the Set System Status command for AT or the Set Private Label command for BT, as shown in the following tables.

Table 2-1. Set System Status for at/af Firmware

[0] KEY	[1] ECHO	[2] SUB	[3] SUB1	[4] SUB2	[5] DATA	[6] DATA	[7] DATA	[8] DATA	[9] DATA	[10] DATA	[11] DATA	[12] DATA
0x00	##	0x07	0x3D	0x01 to 0xFF	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E
Command	—	Global	System Status	Private Label	N	N	N	N	N	N	N	N

Table 2-2. Set Private Label for bt Firmware

[0] KEY	[1] ECHO	[2] SUB	[3] SUB1	[4] SUB2	[5] DATA	[6] DATA	[7] DATA	[8] DATA	[9] DATA	[10] DATA	[11] DATA	[12] DATA
0x00	##	0x07	0x3D	0x01 to 0xFF	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E
Command	—	Global	System Status	RAM Private Label	N	N	N	N	N	N	N	N

This command assists in verifying that a reset has occurred.

RAM Private label: The private label value is 0x00 after reset. It is recommended that any value higher than 0x00 is used when the Host wants to use this field.

The Private Label value can be read by using **Get System Status for bt Firmware** request (see [Table 2-4](#)).

Use the Get System Status command to generate the Private Label value, as shown in the following tables.

Table 2-3. Get System Status for at/af Firmware

[0] KEY	[1] ECHO	[2] SUB	[3] SUB1	[4] SUB2	[5] DATA	[6] DATA	[7] DATA	[8] DATA	[9] DATA	[10] DATA	[11] DATA	[12] DATA
0x02	##	0x07	0x3D	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E
Request	—	Global	System Status	N	N	N	N	N	N	N	N	N
0x03	##	Val	Val	Val	Val	Val	Val	Val	Val	Val	Val	—
Telemetry	—	CPU Status1	CPU Status2	Factory Default	GIE	Private Label	User Byte	Device Fail	Temp Disco	Temp Alarm	Interrupt Register	—

Table 2-4. Get System Status for bt Firmware

[0] KEY	[1] ECHO	[2] SUB	[3] SUB1	[4] SUB2	[5] DATA	[6] DATA	[7] DATA	[8] DATA	[9] DATA	[10] DATA	[11] DATA	[12] DATA
0x02	##	0x07	0xD0	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E
Request	—	Global	BT System Status	N	N	N	N	N	N	N	N	N
0x03	##	Val	Val	Val	Val	Val	Val	Val	0x4E	0x4E	0x4E	Val
Telemetry	—	0x00	CPU Status2 Error Codes	Factory Default	0x00	RAM Private Label	NVM User Byte	Found Devices	N	N	N	Event Exist

2.2 Flash Memory

To support Fast PoE, the PoE settings must be saved in PD69210/PD69220/PD39210 Flash memory. Next time the system will power-up, the latest configuration settings will immediately be loaded by PD692x0 from the Flash memory. Microchip recommends auto-saving the settings every time the user changes the PoE settings. Another option is to allow the user to save the settings manually by command.

To save the settings in the Flash memory, execute the Save System Settings command, as shown in the following table.

Table 2-5. Save System Setting

[0] KEY	[1] ECHO	[2] SUB	[3] SUB1	[4] SUB2	[5] DATA	[6] DATA	[7] DATA	[8] DATA	[9] DATA	[10] DATA	[11] DATA	[12] DATA
0x01	##	0x06	0x0F	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E	0x4E
Program	—	E2	SaveConfig	N	N	N	N	N	N	N	N	N

The Save System Settings command saves the current user values into the non-volatile memory. These user values become the default values after each reset.

Use the Restore Factory Defaults command to change the default values to the initial factory values. For instance, if the host sets the power limit to 400 and this value is a default value, then the Save System Settings command must be executed.

Notes:

- After setting this command, the host must not access the MCU controller using I²C or UART for at least 50 ms.
- The Save System Settings command is not supported by PD69200M.

Important Notes:

- After the firmware update, all settings are reset to the factory defaults and must be saved again.
- Based on Microchip's PD69210/PD69220/PD39210, and not PD69200M.

3. Schematics

For detailed schematics of the PoE system, see application note [AN3361](#).

4. Revision History

Revision	Date	Description
A	04/2021	Document converted to the Microchip format. Document number changed from PD-000362841 to DS-00003979.
2.0	08/2019	PD69220 support was added.
1.0	04/2019	Initial revision.

The Microchip Website

Microchip provides online support via our website at www.microchip.com/. This website is used to make files and information easily available to customers. Some of the content available includes:

- **Product Support** – Data sheets and errata, application notes and sample programs, design resources, user's guides and hardware support documents, latest software releases and archived software
- **General Technical Support** – Frequently Asked Questions (FAQs), technical support requests, online discussion groups, Microchip design partner program member listing
- **Business of Microchip** – Product selector and ordering guides, latest Microchip press releases, listing of seminars and events, listings of Microchip sales offices, distributors and factory representatives

Product Change Notification Service

Microchip's product change notification service helps keep customers current on Microchip products. Subscribers will receive email notification whenever there are changes, updates, revisions or errata related to a specified product family or development tool of interest.

To register, go to www.microchip.com/pcn and follow the registration instructions.

Customer Support

Users of Microchip products can receive assistance through several channels:

- Distributor or Representative
- Local Sales Office
- Embedded Solutions Engineer (ESE)
- Technical Support

Customers should contact their distributor, representative or ESE for support. Local sales offices are also available to help customers. A listing of sales offices and locations is included in this document.

Technical support is available through the website at: www.microchip.com/support

Microchip Devices Code Protection Feature

Note the following details of the code protection feature on Microchip devices:

- Microchip products meet the specifications contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is secure when used in the intended manner and under normal conditions.
- There are dishonest and possibly illegal methods being used in attempts to breach the code protection features of the Microchip devices. We believe that these methods require using the Microchip products in a manner outside the operating specifications contained in Microchip's Data Sheets. Attempts to breach these code protection features, most likely, cannot be accomplished without violating Microchip's intellectual property rights.
- Microchip is willing to work with any customer who is concerned about the integrity of its code.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of its code. Code protection does not mean that we are guaranteeing the product is "unbreakable." Code protection is constantly evolving. We at Microchip are committed to continuously improving the code protection features of our products. Attempts to break Microchip's code protection feature may be a violation of the Digital Millennium Copyright Act. If such acts allow unauthorized access to your software or other copyrighted work, you may have a right to sue for relief under that Act.

Legal Notice

Information contained in this publication is provided for the sole purpose of designing with and using Microchip products. Information regarding device applications and the like is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications.

THIS INFORMATION IS PROVIDED BY MICROCHIP "AS IS". MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION INCLUDING BUT NOT LIMITED TO ANY IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE OR WARRANTIES RELATED TO ITS CONDITION, QUALITY, OR PERFORMANCE.

IN NO EVENT WILL MICROCHIP BE LIABLE FOR ANY INDIRECT, SPECIAL, PUNITIVE, INCIDENTAL OR CONSEQUENTIAL LOSS, DAMAGE, COST OR EXPENSE OF ANY KIND WHATSOEVER RELATED TO THE INFORMATION OR ITS USE, HOWEVER CAUSED, EVEN IF MICROCHIP HAS BEEN ADVISED OF THE POSSIBILITY OR THE DAMAGES ARE FORESEEABLE. TO THE FULLEST EXTENT ALLOWED BY LAW, MICROCHIP'S TOTAL LIABILITY ON ALL CLAIMS IN ANY WAY RELATED TO THE INFORMATION OR ITS USE WILL NOT EXCEED THE AMOUNT OF FEES, IF ANY, THAT YOU HAVE PAID DIRECTLY TO MICROCHIP FOR THE INFORMATION. Use of Microchip devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights unless otherwise stated.

Trademarks

The Microchip name and logo, the Microchip logo, Adaptec, AnyRate, AVR, AVR logo, AVR Freaks, BesTime, BitCloud, chipKIT, chipKIT logo, CryptoMemory, CryptoRF, dsPIC, FlashFlex, flexPWR, HELDO, IGLOO, JukeBlox, KeeLoq, Kleer, LANCheck, LinkMD, maXStylus, maXTouch, MediaLB, megaAVR, Microsemi, Microsemi logo, MOST, MOST logo, MPLAB, OptoLyzer, PackTime, PIC, picoPower, PICSTART, PIC32 logo, PolarFire, Prochip Designer, QTouch, SAM-BA, SenGenuity, SpyNIC, SST, SST Logo, SuperFlash, Symmetricom, SyncServer, Tachyon, TimeSource, tinyAVR, UNI/O, Vectron, and XMEGA are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

AgileSwitch, APT, ClockWorks, The Embedded Control Solutions Company, EtherSynch, FlashTec, Hyper Speed Control, HyperLight Load, IntelliMOS, Libero, motorBench, mTouch, Powermite 3, Precision Edge, ProASIC, ProASIC Plus, ProASIC Plus logo, Quiet-Wire, SmartFusion, SyncWorld, Temux, TimeCesium, TimeHub, TimePictra, TimeProvider, WinPath, and ZL are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Adjacent Key Suppression, AKS, Analog-for-the-Digital Age, Any Capacitor, AnyIn, AnyOut, Augmented Switching, BlueSky, BodyCom, CodeGuard, CryptoAuthentication, CryptoAutomotive, CryptoCompanion, CryptoController, dsPICDEM, dsPICDEM.net, Dynamic Average Matching, DAM, ECAN, Espresso T1S, EtherGREEN, IdealBridge, In-Circuit Serial Programming, ICSP, INICnet, Intelligent Paralleling, Inter-Chip Connectivity, JitterBlocker, maxCrypto, maxView, memBrain, Mindi, MiWi, MPASM, MPF, MPLAB Certified logo, MPLIB, MPLINK, MultiTRAK, NetDetach, Omniscient Code Generation, PICDEM, PICDEM.net, PICKit, PICtail, PowerSmart, PureSilicon, QMatrix, REAL ICE, Ripple Blocker, RTAX, RTG4, SAM-ICE, Serial Quad I/O, simpleMAP, SimpliPHY, SmartBuffer, SMART-I.S., storClad, SQL, SuperSwitcher, SuperSwitcher II, Switchtec, SynchroPHY, Total Endurance, TSHARC, USBCheck, VariSense, VectorBlox, VeriPHY, ViewSpan, WiperLock, XpressConnect, and ZENA are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

The Adaptec logo, Frequency on Demand, Silicon Storage Technology, and Symmcom are registered trademarks of Microchip Technology Inc. in other countries.

GestIC is a registered trademark of Microchip Technology Germany II GmbH & Co. KG, a subsidiary of Microchip Technology Inc., in other countries.

All other trademarks mentioned herein are property of their respective companies.

© 2021, Microchip Technology Incorporated, Printed in the U.S.A., All Rights Reserved.

ISBN: 978-1-5224-8138-6

Quality Management System

For information regarding Microchip's Quality Management Systems, please visit www.microchip.com/quality.

Worldwide Sales and Service

AMERICAS	ASIA/PACIFIC	ASIA/PACIFIC	EUROPE
Corporate Office 2355 West Chandler Blvd. Chandler, AZ 85224-6199 Tel: 480-792-7200 Fax: 480-792-7277 Technical Support: www.microchip.com/support Web Address: www.microchip.com	Australia - Sydney Tel: 61-2-9868-6733 China - Beijing Tel: 86-10-8569-7000 China - Chengdu Tel: 86-28-8665-5511 China - Chongqing Tel: 86-23-8980-9588 China - Dongguan Tel: 86-769-8702-9880 China - Guangzhou Tel: 86-20-8755-8029 China - Hangzhou Tel: 86-571-8792-8115 China - Hong Kong SAR Tel: 852-2943-5100 China - Nanjing Tel: 86-25-8473-2460 China - Qingdao Tel: 86-532-8502-7355 China - Shanghai Tel: 86-21-3326-8000 China - Shenyang Tel: 86-24-2334-2829 China - Shenzhen Tel: 86-755-8864-2200 China - Suzhou Tel: 86-186-6233-1526 China - Wuhan Tel: 86-27-5980-5300 China - Xian Tel: 86-29-8833-7252 China - Xiamen Tel: 86-592-2388138 China - Zhuhai Tel: 86-756-3210040	India - Bangalore Tel: 91-80-3090-4444 India - New Delhi Tel: 91-11-4160-8631 India - Pune Tel: 91-20-4121-0141 Japan - Osaka Tel: 81-6-6152-7160 Japan - Tokyo Tel: 81-3-6880-3770 Korea - Daegu Tel: 82-53-744-4301 Korea - Seoul Tel: 82-2-554-7200 Malaysia - Kuala Lumpur Tel: 60-3-7651-7906 Malaysia - Penang Tel: 60-4-227-8870 Philippines - Manila Tel: 63-2-634-9065 Singapore Tel: 65-6334-8870 Taiwan - Hsin Chu Tel: 886-3-577-8366 Taiwan - Kaohsiung Tel: 886-7-213-7830 Taiwan - Taipei Tel: 886-2-2508-8600 Thailand - Bangkok Tel: 66-2-694-1351 Vietnam - Ho Chi Minh Tel: 84-28-5448-2100	Austria - Wels Tel: 43-7242-2244-39 Fax: 43-7242-2244-393 Denmark - Copenhagen Tel: 45-4485-5910 Fax: 45-4485-2829 Finland - Espoo Tel: 358-9-4520-820 France - Paris Tel: 33-1-69-53-63-20 Fax: 33-1-69-30-90-79 Germany - Garching Tel: 49-8931-9700 Germany - Haan Tel: 49-2129-3766400 Germany - Heilbronn Tel: 49-7131-72400 Germany - Karlsruhe Tel: 49-721-625370 Germany - Munich Tel: 49-89-627-144-0 Fax: 49-89-627-144-44 Germany - Rosenheim Tel: 49-8031-354-560 Israel - Ra'anana Tel: 972-9-744-7705 Italy - Milan Tel: 39-0331-742611 Fax: 39-0331-466781 Italy - Padova Tel: 39-049-7625286 Netherlands - Drunen Tel: 31-416-690399 Fax: 31-416-690340 Norway - Trondheim Tel: 47-72884388 Poland - Warsaw Tel: 48-22-3325737 Romania - Bucharest Tel: 40-21-407-87-50 Spain - Madrid Tel: 34-91-708-08-90 Fax: 34-91-708-08-91 Sweden - Gothenberg Tel: 46-31-704-60-40 Sweden - Stockholm Tel: 46-8-5090-4654 UK - Wokingham Tel: 44-118-921-5800 Fax: 44-118-921-5820