

Interfacing Microchip SPI Serial EEPROMs to NXP P89LPC9XX Microcontrollers Using Hardware Peripheral

*Author: Martin Bowman
Microchip Technology Inc.*


INTRODUCTION

The 25XXX series serial EEPROMs from Microchip Technology are SPI compatible and have maximum clock frequencies ranging from 3 MHz to 20 MHz. Many times when designing an application which utilizes a serial EEPROM device, it may be beneficial to use a microcontroller which features a hardware peripheral. This often offers a faster serial bus and a quicker time to market, in addition to reduction in code size.

This application note provides assistance and source code to ease the design process of interfacing an NXP P89LPC952 microcontroller to a Microchip SPI serial EEPROM, using the hardware serial port.

Figure 1 describes the hardware schematic for the interface between Microchip's 25XXX series devices and the P89LPC9XX microcontroller. The schematic shows the connections necessary between the microcontroller and the serial EEPROM as tested, and the software was written assuming these connections. The CS, WP and HOLD pins are tied to VCC through resistors because the write-protect and hold features are not used in the examples provided. The CS pin is also tied to VCC via a 10K resistor. This is not required but considered good practice.

FIGURE 1: CIRCUIT FOR P89LPC9XX AND 25XXX SERIES DEVICE



FIRMWARE DESCRIPTION

The purpose of the program is to show individual features of the SPI protocol and give code samples of the instructions and addressing schemes so that the basic building blocks of a program can be shown. The firmware performs the following operations:

- Low Density Byte Write
- Low Density Byte Read
- Low Density Page Write
- Low Density Sequential Read
- Write Enable
- WIP Polling

In addition, the following operations are available but not explicitly illustrated:

- High Density Byte Write
- High Density Byte Read
- High Density Page Write
- High Density Sequential Read
- Write Disable
- Read Status Register
- Write Status Register

The low density routines are intended for use with the 4K and smaller density devices that use only one byte for addressing. The high density routines are intended for use with 8K and higher density devices that use two bytes for addressing. This program also exhibits the WIP polling feature for detecting the completion of write cycles after the byte write and page write operations. Read operations are located directly after each write operation, thus allowing for verification that the data was properly written. No method of displaying the input data is provided, but a SEEVAL[®] 32 evaluation system, or an oscilloscope is recommended.

The low-density code was tested using the 25LC040A serial EEPROM. This device features 512 x 8 (4 Kbit) of memory and 16-byte pages. The high-density code was tested using the 25LC256 serial EEPROM. This device features 32K x 8 (256 Kbit) of memory and 64-byte pages. Only the low-density operations are illustrated in this application note.


Oscilloscope screen shots are labeled for ease in reading. The data sheet version of the waveforms are shown below the oscilloscope screen shots. All timings are designed to meet the data sheet specs, and the internal oscillator is used to clock the P89LPC9XX. If a different clock is used, the code may need to be modified to avoid violating timing specs. All values represented in this application note are decimal values unless otherwise noted, and are for guidance only.

WRITE ENABLE

Figure 2 shows an example of the Write Enable command. Chip Select is brought low (active) and the opcode (0x06) is shifted out. The Write Enable command must be given in order to set the WEL bit before

a write is attempted to either the array or the STATUS register. The WEL bit can be cleared by issuing a Write Disable command (WRDI) and is also automatically reset if the device is powered down or if a write cycle is completed.

FIGURE 2: WRITE ENABLE (WREN)




READ STATUS REGISTER TO CHECK FOR WEL BIT

Figure 3 shows an example of the Read Status Register command to check for the WEL bit. This bit must be set before a write is attempted to either the STATUS register or the array. It is good programming practice to check for the bit to be set before attempting the write. Once again the device is selected and the opcode (0x05) is sent.

The STATUS register is shifted out on the Serial Out pin. A value of 0x02 shows that the WEL bit in the STATUS register has been set. The device is now ready to do a write to either the STATUS register or the array.

FIGURE 3: READ STATUS REGISTER TO CHECK FOR WEL BIT (RDSR)




BYTE WRITE COMMAND (OPCODE, ADDRESS AND DATA)

Figure 4 shows an example of the Write command. First, the device is selected by bringing Chip Select low (active). In this example, the Most Significant bit of the address is a '1'. This bit is embedded in the opcode (0x02 for a Write command), and so the value 0x0A is sent. The Low Address byte (0x33) is sent next. Finally, the data is clocked in last, in this case 0xCC. Once Chip Select is toggled at the end of this command, the internal write cycle is initiated. After the write cycle has begun, the WIP bit in the STATUS register can be polled to check when the write finishes. If polling is not used, a delay (~5ms) needs to be added to ensure the write has finished. This code uses WIP polling.

A page write can be accomplished by continuing to send data bytes to the device without toggling $\overline{\text{CS}}$. Up to 16 bytes can be written to the 25LC040A before a write cycle is needed. Once $\overline{\text{CS}}$ is brought high after the data bytes have been transmitted, then the write cycle timer will begin and normal polling can be initiated.

The Page Write function provided in the firmware is used to program 16 bytes of data, starting at address 0x150. Because page writes cannot cross page boundaries, care must be taken to avoid having data wrap around to the beginning of the page and overwrite existing data.

FIGURE 4: BYTE WRITE COMMAND, ADDRESS AND DATA




DATA POLLING (RDSR – CHECK FOR WIP SET)

After a valid Write command is given, the STATUS register can be read to check if the internal write cycle has been initiated, and it can continuously be monitored to look for the end of the write cycle. In this

case, the device is selected and the RDSR opcode (0x05) is sent. The STATUS register is then shifted out on the Serial Out (SO) pin resulting in a value of 0x03. Figure 5 shows that both the WEL bit (bit 1) and the WIP bit (bit 0) are set, meaning that the write cycle is in progress.


FIGURE 5: DATA POLLING (READ STATUS REGISTER TO CHECK WIP BIT)



DATA POLLING FINISHED (RDSR – WIP BIT CLEARED)

The firmware remains in a continuous loop and the WIP status is evaluated until the bit is cleared. Figure 6 shows the Read Status Register command followed by a value of 0x00 being shifted out on the Serial Out (SO) pin. This indicates that the write cycle has finished and the device is now ready for additional commands. The WEL bit is also cleared at the end of a write cycle, which serves as additional protection against unwanted writes.

FIGURE 6: DATA POLLING FINISHED (RDSR – WIP AND WEL BITS CLEARED)




READ COMMAND (OPCODE, ADDRESS AND DATA)

Figure 7 shows an example of the Read command. For this, the device is selected. As with the Write command, the Most Significant bit of the address is a '1'. Therefore, when combined with the Read opcode (0x03), the value 0x0B is sent. The Low Address byte, 0x33, is

then sent. Finally the data, 0xCC in this case, is clocked out on the Serial Out (SO) pin. In order to perform a sequential read, more clocks need to be generated. It is possible to read the entire chip by continuing to clock the device. Once the end of the array is reached, the data will wrap to the beginning of the array (address 0x000) and keep reading out until $\overline{\text{CS}}$ is deselected or the device is no longer being clocked.

FIGURE 7: READ COMMAND, ADDRESS AND DATA



CONCLUSION

These are some of the basic features of SPI communications on one of LPC 8051 devices from NXP with the use of a hardware serial port. The code is highly portable and can be used on many 8051 derivatives with very minor modifications. Using the code provided, designers can begin to build their own SPI libraries to be as simple or as complex as needed. The code was tested on the Keil MCB950 Demonstration Board with the connections shown in Figure 1.

NOTES:

Note the following details of the code protection feature on Microchip devices:

- Microchip products meet the specification contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is one of the most secure families of its kind on the market today, when used in the intended manner and under normal conditions.
- There are dishonest and possibly illegal methods used to breach the code protection feature. All of these methods, to our knowledge, require using the Microchip products in a manner outside the operating specifications contained in Microchip's Data Sheets. Most likely, the person doing so is engaged in theft of intellectual property.
- Microchip is willing to work with the customer who is concerned about the integrity of their code.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of their code. Code protection does not mean that we are guaranteeing the product as "unbreakable."

Code protection is constantly evolving. We at Microchip are committed to continuously improving the code protection features of our products. Attempts to break Microchip's code protection feature may be a violation of the Digital Millennium Copyright Act. If such acts allow unauthorized access to your software or other copyrighted work, you may have a right to sue for relief under that Act.

Information contained in this publication regarding device applications and the like is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications. MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION, INCLUDING BUT NOT LIMITED TO ITS CONDITION, QUALITY, PERFORMANCE, MERCHANTABILITY OR FITNESS FOR PURPOSE. Microchip disclaims all liability arising from this information and its use. Use of Microchip devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights.

Trademarks

The Microchip name and logo, the Microchip logo, Accuron, dsPIC, KEELoQ, KEELoQ logo, microID, MPLAB, PIC, PICmicro, PICSTART, PRO MATE, PowerSmart, rPIC, and SmartShunt are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

Amplab, FilterLab, Linear Active Thermistor, Migratable Memory, MXDEV, MXLAB, PS logo, SEEVAL, SmartSensor and The Embedded Control Solutions Company are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Analog-for-the-Digital Age, Application Maestro, CodeGuard, dsPICDEM, dsPICDEM.net, dsPICworks, ECAN, ECONOMONITOR, FanSense, FlexROM, fuzzyLAB, In-Circuit Serial Programming, ICSP, ICEPIC, Mindi, MiWi, MPASM, MPLAB Certified logo, MPLIB, MPLINK, PICkit, PICDEM, PICDEM.net, PICLAB, PICtail, PowerCal, PowerInfo, PowerMate, PowerTool, REAL ICE, rLAB, rfPICDEM, Select Mode, Smart Serial, SmartTel, Total Endurance, UNI/O, WiperLock and ZENA are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

All other trademarks mentioned herein are property of their respective companies.

© 2007, Microchip Technology Incorporated, Printed in the U.S.A., All Rights Reserved.

 Printed on recycled paper.

QUALITY MANAGEMENT SYSTEM
CERTIFIED BY DNV
== ISO/TS 16949:2002 ==

Microchip received ISO/TS-16949:2002 certification for its worldwide headquarters, design and wafer fabrication facilities in Chandler and Tempe, Arizona, Gresham, Oregon and Mountain View, California. The Company's quality system processes and procedures are for its PIC® MCUs and dsPIC® DSCs, KEELoQ® code hopping devices, Serial EEPROMs, microperipherals, nonvolatile memory and analog products. In addition, Microchip's quality system for the design and manufacture of development systems is ISO 9001:2000 certified.



WORLDWIDE SALES AND SERVICE

AMERICAS

Corporate Office
2355 West Chandler Blvd.
Chandler, AZ 85224-6199
Tel: 480-792-7200
Fax: 480-792-7277
Technical Support:
<http://support.microchip.com>
Web Address:
www.microchip.com

Atlanta
Duluth, GA
Tel: 678-957-9614
Fax: 678-957-1455

Boston
Westborough, MA
Tel: 774-760-0087
Fax: 774-760-0088

Chicago
Itasca, IL
Tel: 630-285-0071
Fax: 630-285-0075

Dallas
Addison, TX
Tel: 972-818-7423
Fax: 972-818-2924

Detroit
Farmington Hills, MI
Tel: 248-538-2250
Fax: 248-538-2260

Kokomo
Kokomo, IN
Tel: 765-864-8360
Fax: 765-864-8387

Los Angeles
Mission Viejo, CA
Tel: 949-462-9523
Fax: 949-462-9608

Santa Clara
Santa Clara, CA
Tel: 408-961-6444
Fax: 408-961-6445

Toronto
Mississauga, Ontario,
Canada
Tel: 905-673-0699
Fax: 905-673-6509

ASIA/PACIFIC

Asia Pacific Office
Suites 3707-14, 37th Floor
Tower 6, The Gateway
Harbour City, Kowloon
Hong Kong
Tel: 852-2401-1200
Fax: 852-2401-3431

Australia - Sydney
Tel: 61-2-9868-6733
Fax: 61-2-9868-6755

China - Beijing
Tel: 86-10-8528-2100
Fax: 86-10-8528-2104

China - Chengdu
Tel: 86-28-8665-5511
Fax: 86-28-8665-7889

China - Fuzhou
Tel: 86-591-8750-3506
Fax: 86-591-8750-3521

China - Hong Kong SAR
Tel: 852-2401-1200
Fax: 852-2401-3431

China - Qingdao
Tel: 86-532-8502-7355
Fax: 86-532-8502-7205

China - Shanghai
Tel: 86-21-5407-5533
Fax: 86-21-5407-5066

China - Shenyang
Tel: 86-24-2334-2829
Fax: 86-24-2334-2393

China - Shenzhen
Tel: 86-755-8203-2660
Fax: 86-755-8203-1760

China - Shunde
Tel: 86-757-2839-5507
Fax: 86-757-2839-5571

China - Wuhan
Tel: 86-27-5980-5300
Fax: 86-27-5980-5118

China - Xian
Tel: 86-29-8833-7250
Fax: 86-29-8833-7256

ASIA/PACIFIC

India - Bangalore
Tel: 91-80-4182-8400
Fax: 91-80-4182-8422

India - New Delhi
Tel: 91-11-4160-8631
Fax: 91-11-4160-8632

India - Pune
Tel: 91-20-2566-1512
Fax: 91-20-2566-1513

Japan - Yokohama
Tel: 81-45-471- 6166
Fax: 81-45-471-6122

Korea - Gumi
Tel: 82-54-473-4301
Fax: 82-54-473-4302

Korea - Seoul
Tel: 82-2-554-7200
Fax: 82-2-558-5932 or
82-2-558-5934

Malaysia - Penang
Tel: 60-4-646-8870
Fax: 60-4-646-5086

Philippines - Manila
Tel: 63-2-634-9065
Fax: 63-2-634-9069

Singapore
Tel: 65-6334-8870
Fax: 65-6334-8850

Taiwan - Hsin Chu
Tel: 886-3-572-9526
Fax: 886-3-572-6459

Taiwan - Kaohsiung
Tel: 886-7-536-4818
Fax: 886-7-536-4803

Taiwan - Taipei
Tel: 886-2-2500-6610
Fax: 886-2-2508-0102

Thailand - Bangkok
Tel: 66-2-694-1351
Fax: 66-2-694-1350

EUROPE

Austria - Wels
Tel: 43-7242-2244-39
Fax: 43-7242-2244-393

Denmark - Copenhagen
Tel: 45-4450-2828
Fax: 45-4485-2829

France - Paris
Tel: 33-1-69-53-63-20
Fax: 33-1-69-30-90-79

Germany - Munich
Tel: 49-89-627-144-0
Fax: 49-89-627-144-44

Italy - Milan
Tel: 39-0331-742611
Fax: 39-0331-466781

Netherlands - Drunen
Tel: 31-416-690399
Fax: 31-416-690340

Spain - Madrid
Tel: 34-91-708-08-90
Fax: 34-91-708-08-91

UK - Wokingham
Tel: 44-118-921-5869
Fax: 44-118-921-5820