

# Choosing Atmel ATF150xASV(L) POR Options

## Summary

Atmel EPLDs are capable of operation down to the reset level,  $V_{RST}$ . In 5.0V devices,  $V_{RST}$  generally is midway between the specified minimum power supply voltage and 0.0V, and so the margin for droop, noise, etc. is sufficient. In low voltage devices,  $V_{RST}$  is generally just below the specified minimum power supply voltage, and available margin is reduced. In applications where the supply voltage falls close to the specified minimum power supply voltage, Atmel recommends increasing the margin for falling  $V_{CC}$ . In the ATF150xASV(L) family, Atmel recommends changing the Power\_On\_Reset hysteresis from small to large. Methods and means of implementing this recommendation are discussed.

## Details

All Atmel EPLDs are designed with a power-up reset function to initialize all registers at a point delayed slightly from  $V_{CC}$  rising above  $V_{RST}$ . Similarly, if  $V_{CC}$  falls below  $V_{RST}$ , the device will return to the reset state. Due to the asynchronous nature of reset and uncertainty of how  $V_{CC}$  actually rises in the system, the following conditions are required:

1. The  $V_{CC}$  rise must be monotonic.
2. After reset occurs, all input and feedback setup times must be met before driving the clock pin high.
3. The clock must remain stable during  $T_D$ .

The Atmel ATF150xASV family of 3.3V parts offers the user a programmable option for the hysteresis about the reset level, small or large. In the case of the Atmel ATF150xASV family, nominal  $V_{CC}$  is 3.3V, the minimum  $V_{CC}$  is 3.0V and the default small hysteresis choice puts the  $V_{RST}$  level just below minimum  $V_{CC}$  for both rising and falling  $V_{CC}$ .

To ensure a robust operating environment in these cases, Atmel recommends that users set the power-up reset hysteresis to large. With the large hysteresis option selected, the reset level for falling  $V_{CC}$  drops to a lower level, increasing the margin before the device returns to the reset state.

- Synario users should open the Properties dialog box and change setting of the Power\_On\_Reset Hysteresis from the default “Small” to “Large” before running the Fitting process.
- Atmel POF2JED users should include the flag “-power\_reset” on the command line after “filename.POF” when running conversions.

To ensure that the registers are properly re-initialized when  $V_{CC}$  rises again, the following condition is added:

4. If  $V_{CC}$  falls below 2.0V, it must shut off completely before the device is turned on again.

With the hysteresis option set to large,  $I_{CC}$  is reduced several hundred  $\mu A$ . This is especially significant for the “ATF150xASL” versions because it brings the standby  $I_{CC}$  down to the  $\mu A$  level.



EPLD

Technical  
Bulletin





## **Atmel Headquarters**

### ***Corporate Headquarters***

2325 Orchard Parkway  
San Jose, CA 95131  
TEL (408) 441-0311  
FAX (408) 487-2600

### ***Europe***

Atmel SarL  
Route des Arsenaux 41  
Casa Postale 80  
CH-1705 Fribourg  
Switzerland  
TEL (41) 26-426-5555  
FAX (41) 26-426-5500

### ***Asia***

Atmel Asia, Ltd.  
Room 1219  
Chinachem Golden Plaza  
77 Mody Road Tsimhatsui  
East Kowloon  
Hong Kong  
TEL (852) 2721-9778  
FAX (852) 2722-1369

### ***Japan***

Atmel Japan K.K.  
9F, Tonetsu Shinkawa Bldg.  
1-24-8 Shinkawa  
Chuo-ku, Tokyo 104-0033  
Japan  
TEL (81) 3-3523-3551  
FAX (81) 3-3523-7581

## **Atmel Operations**

### ***Atmel Colorado Springs***

1150 E. Cheyenne Mtn. Blvd.  
Colorado Springs, CO 80906  
TEL (719) 576-3300  
FAX (719) 540-1759

### ***Atmel Rousset***

Zone Industrielle  
13106 Rousset Cedex  
France  
TEL (33) 4-4253-6000  
FAX (33) 4-4253-6001

### ***Atmel Smart Card ICs***

Scottish Enterprise Technology Park  
East Kilbride, Scotland G75 0QR  
TEL (44) 1355-803-000  
FAX (44) 1355-242-743

### ***Atmel Grenoble***

Avenue de Rochepleine  
BP 123  
38521 Saint-Egreve Cedex  
France  
TEL (33) 4-7658-3000  
FAX (33) 4-7658-3480

---

### ***Atmel EPLD Hotline***

1-(408) 436-4333

### ***Atmel EPLD e-mail***

pld@atmel.com

### ***Atmel EPLD Fax***

1-(408) 487-2664

---

### ***Fax-on-Demand***

North America:

1-(800) 292-8635

International:

1-(408) 441-0732

### ***e-mail***

literature@atmel.com

### ***Web Site***

<http://www.atmel.com>

### ***BBS***

1-(408) 436-4309

## **© Atmel Corporation 2000.**

Atmel Corporation makes no warranty for the use of its products, other than those expressly contained in the Company's standard warranty which is detailed in Atmel's Terms and Conditions located on the Company's web site. The Company assumes no responsibility for any errors which may appear in this document, reserves the right to change devices or specifications detailed herein at any time without notice, and does not make any commitment to update the information contained herein. No licenses to patents or other intellectual property of Atmel are granted by the Company in connection with the sale of Atmel products, expressly or by implication. Atmel's products are not authorized for use as critical components in life support devices or systems.

Marks bearing ® and/or ™ are registered trademarks and trademarks of Atmel Corporation.

Terms and product names in this document may be trademarks of others.



Printed on recycled paper.