

Clock System Configuration and Usage on SAM E5x (Cortex M4) Devices

TB3226



Introduction

The SAM E5x family of microcontrollers (MCUs) contains a sophisticated clock distribution system designed to give maximum flexibility to the user application. The clock system allows the tuning of the performance and power consumption of the device in a dynamic manner to achieve the best trade-off between the two for an application.

The following figure illustrates the clock management diagram of the SAM E54 MCU.

Figure 1. SAM E54 Clock Distribution




Table of Contents

Introduction.....	1
1. Description.....	3
2. Clock Synchronization.....	4
3. Power and Performance Considerations.....	5
4. Configuring Clocks with MPLAB Harmony v3.....	6
4.1. Use Case Scenarios.....	6
5. Resources.....	11
6. Revision History.....	12
Microchip Information.....	13
The Microchip Website.....	13
Product Change Notification Service.....	13
Customer Support.....	13
Microchip Devices Code Protection Feature.....	13
Legal Notice.....	13
Trademarks.....	14
Quality Management System.....	15
Worldwide Sales and Service.....	16

1. Description

The clock system of the SAM E54 MCU consists of the following blocks:

Clock Sources

The SAM E54 MCU has several clock source modules. The supported clock source modules are as follows:

OSCCTRL: High frequency clock sources

- XOSCn – 8 to 48 MHz External Oscillator
- DFLL48M – 48 MHz Internal Oscillator (Open Loop)
- FDDLn – 96 to 200 MHz Fractional Digital Phase Locked Loop Oscillator

OSCK32CTRL: Low-frequency clock sources

- XOSC32K – 32 kHz External Crystal Oscillator, provides both 32 kHz and 1.024 kHz clock outputs
- OSCULP32K – 32 kHz Internal Crystal Oscillator, provides both 32 kHz and 1.024 kHz clock outputs

Generic Clock Controller (GCLK)

The GCLK provides Generic Clocks to various peripheral clock domains. The GCLK consists of 12 GCLK generators and 48 peripheral channels. The GCLK_IO (Generic Clock Controller Input/Output) blocks act as a clock source to the GCLK generators.

Notes:

1. GCLK_IO[x] is Generic Input/Output External Clock Signal.
2. GCLK1 is the output of the GCLK generator 1, and is one of the clock sources for all GCLK generators except GCLK generator 1.

The GCLK Generators consists of programmable prescaler. The programmable prescaler scales down the input frequency from one of the Clock Sources (as discussed above) to a slower rate to use with a peripheral.

The peripheral channels multiplex and gate various generator outputs to one or more peripherals within the device. This setup allows a single common generator to feed one or more peripheral channels, which can then be enabled or disabled individually as required.

Main Clock Controller (MCLK)

The MCLK also known as the Synchronous Clock Controller provides the synchronous clocks (CPU, bus (AHB, APB) clocks) to the system. The main clock GCLK_MAIN to the MCLK is fed from the GCLK generator 0 through peripheral channel 0. The MCLK contains clock masks that can turn on and off the user interface of a peripheral as well as prescalers for the CPU clocks.


2. Clock Synchronization

The peripherals on the SAM E54 MCU composed of the following two clock domain interfaces:

- Synchronous interface: It is connected to the AHB/APB bus running from the synchronous clock in the Main clock (MCLK) domain. The CPU accesses the peripheral registers through the synchronous interface.
- Asynchronous interface: It is connected to the core peripheral running from the asynchronous peripheral Generic Clock (GCLK) domain. The core peripheral runs at the asynchronous peripheral generic clock.

Communication between these clock domains must be synchronized. This mechanism is implemented in the hardware through the SYNCBUSY peripheral status register. The synchronization process takes place even if the peripheral generic clock is running from the same clock source and on the same frequency as the bus interface.

Figure 2-1. Clock Synchronization



3. Power and Performance Considerations

In an application, the system and peripheral clock frequencies are configured based on the power and performance requirements of the application. Power consumption of a device is directly proportional to the frequency of operation. A device running at high speeds consumes more power versus a device running at low speed.

For SAM E54 MCU, refer to the chapter “Electrical Characteristics” of the device data sheet for power and performance values.

Each GCLK generator operates independently, enabling the GCLK generators to drive different clock frequencies for different peripherals, and to drive different clock frequencies for different instances of the same peripheral. This capability of the GCLK generators enable power saving, hence only the necessary clocks are generated. In Power Saving mode of the MCU, when a peripheral is not utilizing the peripheral clock, the GCLK generator will not source from the oscillator until the peripheral requests the clock.

As noted above, the peripherals on the SAM E5x devices run on the asynchronous clock domain. These asynchronous peripheral clocks are synchronized to the system clocks (CPU, AHB/APB) when the CPU accesses the peripheral registers. The synchronization time is an important factor in the overall response time of the system.

For example, running a peripheral with a very low speed has a lower active power consumption. However, at the same time, the synchronization to the synchronous clock domain is dependent on the peripheral clock speed. The slower peripheral clock leads to lower response time and needs more wait time for the synchronization to complete.

4. Configuring Clocks with MPLAB Harmony v3

MPLAB® Harmony is a modular framework that provides interoperable firmware libraries for application development on 32-bit microcontrollers and microprocessors. It includes an easy to use graphical user interface, MPLAB Code Configurator (MCC) for selection, configuration, generation of starter code, peripheral libraries, and middleware (USB, TCP/IP, graphics, and so on). The MCC provides an easy to use UI window, Clock easy View, to configure system and peripheral clocks.


For detailed information on MPLAB Harmony v3 refer to: www.microchip.com/en-us/tools-resources/configure/mplab-harmony.

4.1 Use Case Scenarios

The following use case scenarios demonstrate how to use the MCC Clock Configuration plugin to configure the clocks.

1. To launch Clock Easy View in MPLAB X IDE, click on the **Project Graphs** tab, and then from the Plugins drop-down item list select **Clock Configuration**.

Figure 4-1. Harmony 3 Clock Configuration Launcher




2. Click on the **Clock Easy View** tab to launch the Clock Easy View.

Use Case Scenario 1

Configure the device to run at a maximum possible speed. Measure the frequency of the configured clock by routing a prescaled clock signal to a GPIO pin.

1. SAME54 operates at 120 MHz maximum frequency. One of the FDPLL must be configured and enabled to run the main clock at the maximum frequency. All clocks in the system are routed through the GCLK generators, therefore the configured FDPLL must be fed as input to the GCLK0 generator and a suitable clock divider and masker must be selected to achieve the maximum frequency (120 MHz). Refer to the following figure to configure the main clock.

Figure 4-2. Harmony 3 Main Clock Configuration




Follow these steps to configure the system to run at maximum frequency:

1. Configure and enable the DFLL in open-loop mode to generate 48 MHz.
2. Configure and enable the GCLK2 to generate 1 MHz from the DFLL.
3. Configure and enable the FDPLL0 to generate 120 MHz using the GCLK2 and feed this FDPLL output to the GCLK0 by selecting the FDPLL0 as the source. The Main Clock will be derived from the GCLK0.




Tip: Double-click on the Clock Easy View tab to maximize the window.

2. Enable the GCLK generator 1 and select the oscillator FDPLL0 as generator input. The divider value of a generator will be used to derive the lower frequency clocks from the GCLK generator. Configure the divider value as 12 to achieve a 10 MHz clock frequency at the GCLK generator 1. The output is shown in the figure below. Refer to the "SAM D5x/E5x Family Data Sheet" for the maximum clock frequency an I/O pin can operate at.

Figure 4-3. Clock Divider Configuration

3. This output can be used to measure the frequency and accuracy of the main clock. Click **GCLK I/O Configuration** to check the configured GCLK I/O [1] clock frequency, see figure below.

Figure 4-4. GCLK I/O Configuration


4. Configure the pin, which maps to GCLK1 on the device. To configure clock signal GCLK1 to a pin, use the Pin Configuration option in MCC.
5. To launch Pin Configuration in MPLAB X IDE, click on the **Project Graphs** tab, and then from the Plugins drop-down item list select **Pin Configuration**.

Use Case Scenario 2

Configure the SERCOM peripheral clock to run the SERCOM (as USART) peripheral.


1. Configure the main clock, as shown in "Step 1" of the Use Case Scenario 1.
2. By default, MCC automatically enables the peripheral, APB and AHB clocks, when a peripheral is added to the project graph. Click **Peripheral Clock Configuration** to verify the specific peripheral (SERCOM) clock. The SERCOM0 clock source is selected as GLCK1, which is set to 10 MHz, see figure below.

Figure 4-5. SERCOM Peripheral Clock



- The Peripheral Clock Configuration window can be used to configure the peripheral to run at a frequency different from the default frequency (10 MHz). A different clock source can be selected. Refer to the figure below to configure the SERCOM0 peripheral clock with 60 MHz frequency by using the GCLK3 as a source.

Figure 4-6. SERCOM Peripheral Clock Configuration




- Configure the SERCOM (as USART) pins on the device. To configure the SERCOM (as USART) pins, use the Pin Configuration option in the MCC. To launch Pin Configuration, click on the **Project Graphs** tab, and then from the Plugins drop-down item list select **PinConfiguration**.

Use Case Scenario 3

Follow these steps to configure the RTC peripheral clock in MPLAB Harmony 3 to run the RTC peripheral at low power.

1. Configure the main clock, as shown in “Step 1” of the Use Case Scenario 1.
2. On SAME54, some of the peripherals, such as the RTC, WDT, and EIC will run directly with the 32 KHz oscillator controller outputs (OSCULP32K, OSCULP1K (see Note 3), XOSC32K, XOSC1K).
3. While selecting the OSCULP1K oscillator as the RTC peripheral clock input, the RTC will run at low power. The OSCULP1K oscillator will provide a 1 KHz clock frequency as the oscillator output by running at low power. Refer to the figure below to configure the RTC peripheral clock.

Figure 4-7. RTC Peripheral Clock Configuration



4. The RTC peripheral can be used for different applications. For example, the RTC used as a calendar requires an accurate clock source. When the RTC is used as a calendar, it uses an external accurate clock source. The external clock sources (XOSC1K or XOSC32K) can be configured in the MCC.

Notes:

1. Advanced clock configuration options, such as RUN in STANDBY, ONDEMAND clock, DPLL COARSE, FINE can be configured in the clock tree view. In MCC, go to *Project graph > System > Clock*.
2. In the use case scenarios above, the MCC UI screen shots are captured using MPLAB Code Configurator v5.5.7 and repositories Chip Support Package (CSP) v3.18.0.
3. OSCULP1K is an Oscillator name used in MPLAB Code Configurator for 1.024 kHz output from 32 kHz internal Oscillator.

5. Resources

For additional information on clock systems and low-power features, refer to the following documents:

- Tech Brief: What is SleepWalking? How it Helps to Reduce Power Consumption: ww1.microchip.com/downloads/en/DeviceDoc/90003183A.pdf
- Training module: Low Power Application on SAM E54 (Arm® Cortex®-M4) MCUs Using MPLAB® Harmony v3 Peripheral Libraries: microchipdeveloper.com/xwiki/bin/view/software-tools/harmony/low-power-application-on-sam-e54/
- For additional info about 32-bit Microcontroller Collaterals and Solutions, refer to: ww1.microchip.com/downloads/aemDocuments/documents/MCU32/ProductDocuments/ReferenceManuals/32-bit-Microcontroller-Collateral-and-Solutions-Reference-Guide-DS70005534.pdf

6. Revision History

Revision B - January 2024

The following updates were incorporated for this revision:

Document	Minor changes of format. Changed <i>MPLAB Harmony Configurator</i> by <i>MPLAB Code Configurator</i> . Changed <i>MHC</i> by <i>MCC</i> .
4. Configuring Clocks with MPLAB Harmony v3	Updated some paragraphs in 4.1. Use Case Scenarios . Updated Figure 4-1 , Figure 4-2 , Figure 4-5 , Figure 4-6 and Figure 4-7 .
5. Resources	Added new references.

Revision A - August 2019

This is the initial released version of this document.

Microchip Information

The Microchip Website

Microchip provides online support via our website at www.microchip.com/. This website is used to make files and information easily available to customers. Some of the content available includes:

- **Product Support** – Data sheets and errata, application notes and sample programs, design resources, user's guides and hardware support documents, latest software releases and archived software
- **General Technical Support** – Frequently Asked Questions (FAQs), technical support requests, online discussion groups, Microchip design partner program member listing
- **Business of Microchip** – Product selector and ordering guides, latest Microchip press releases, listing of seminars and events, listings of Microchip sales offices, distributors and factory representatives

Product Change Notification Service

Microchip's product change notification service helps keep customers current on Microchip products. Subscribers will receive email notification whenever there are changes, updates, revisions or errata related to a specified product family or development tool of interest.

To register, go to www.microchip.com/pcn and follow the registration instructions.

Customer Support

Users of Microchip products can receive assistance through several channels:

- Distributor or Representative
- Local Sales Office
- Embedded Solutions Engineer (ESE)
- Technical Support

Customers should contact their distributor, representative or ESE for support. Local sales offices are also available to help customers. A listing of sales offices and locations is included in this document.

Technical support is available through the website at: www.microchip.com/support

Microchip Devices Code Protection Feature

Note the following details of the code protection feature on Microchip products:

- Microchip products meet the specifications contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is secure when used in the intended manner, within operating specifications, and under normal conditions.
- Microchip values and aggressively protects its intellectual property rights. Attempts to breach the code protection features of Microchip product is strictly prohibited and may violate the Digital Millennium Copyright Act.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of its code. Code protection does not mean that we are guaranteeing the product is "unbreakable". Code protection is constantly evolving. Microchip is committed to continuously improving the code protection features of our products.

Legal Notice

This publication and the information herein may be used only with Microchip products, including to design, test, and integrate Microchip products with your application. Use of this information in any other manner violates these terms. Information regarding device applications is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure

that your application meets with your specifications. Contact your local Microchip sales office for additional support or, obtain additional support at www.microchip.com/en-us/support/design-help/client-support-services.

THIS INFORMATION IS PROVIDED BY MICROCHIP "AS IS". MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION INCLUDING BUT NOT LIMITED TO ANY IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE, OR WARRANTIES RELATED TO ITS CONDITION, QUALITY, OR PERFORMANCE.

IN NO EVENT WILL MICROCHIP BE LIABLE FOR ANY INDIRECT, SPECIAL, PUNITIVE, INCIDENTAL, OR CONSEQUENTIAL LOSS, DAMAGE, COST, OR EXPENSE OF ANY KIND WHATSOEVER RELATED TO THE INFORMATION OR ITS USE, HOWEVER CAUSED, EVEN IF MICROCHIP HAS BEEN ADVISED OF THE POSSIBILITY OR THE DAMAGES ARE FORESEEABLE. TO THE FULLEST EXTENT ALLOWED BY LAW, MICROCHIP'S TOTAL LIABILITY ON ALL CLAIMS IN ANY WAY RELATED TO THE INFORMATION OR ITS USE WILL NOT EXCEED THE AMOUNT OF FEES, IF ANY, THAT YOU HAVE PAID DIRECTLY TO MICROCHIP FOR THE INFORMATION.

Use of Microchip devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights unless otherwise stated.

Trademarks

The Microchip name and logo, the Microchip logo, Adaptec, AVR, AVR logo, AVR Freaks, BesTime, BitCloud, CryptoMemory, CryptoRF, dsPIC, flexPWR, HELDO, IGLOO, JukeBlox, KeeLoq, Kleer, LANCheck, LinkMD, maXStylus, maXTouch, MediaLB, megaAVR, Microsemi, Microsemi logo, MOST, MOST logo, MPLAB, OptoLyzer, PIC, picoPower, PICSTART, PIC32 logo, PolarFire, Prochip Designer, QTouch, SAM-BA, SenGenuity, SpyNIC, SST, SST Logo, SuperFlash, Symmetricom, SyncServer, Tachyon, TimeSource, tinyAVR, UNI/O, Vectron, and XMEGA are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

AgileSwitch, ClockWorks, The Embedded Control Solutions Company, EtherSynch, Flashtec, Hyper Speed Control, HyperLight Load, Libero, motorBench, mTouch, Powermite 3, Precision Edge, ProASIC, ProASIC Plus, ProASIC Plus logo, Quiet-Wire, SmartFusion, SyncWorld, TimeCesium, TimeHub, TimePictra, TimeProvider, and ZL are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Adjacent Key Suppression, AKS, Analog-for-the-Digital Age, Any Capacitor, AnyIn, AnyOut, Augmented Switching, BlueSky, BodyCom, Clockstudio, CodeGuard, CryptoAuthentication, CryptoAutomotive, CryptoCompanion, CryptoController, dsPICDEM, dsPICDEM.net, Dynamic Average Matching, DAM, ECAN, Espresso T1S, EtherGREEN, EyeOpen, GridTime, IdealBridge, IGaT, In-Circuit Serial Programming, ICSP, INICnet, Intelligent Paralleling, IntelliMOS, Inter-Chip Connectivity, JitterBlocker, Knob-on-Display, MarginLink, maxCrypto, maxView, memBrain, Mindi, MiWi, MPASM, MPF, MPLAB Certified logo, MPLIB, MPLINK, mSiC, MultiTRAK, NetDetach, Omniscient Code Generation, PICDEM, PICDEM.net, PICKit, PICtail, Power MOS IV, Power MOS 7, PowerSmart, PureSilicon, QMatrix, REAL ICE, Ripple Blocker, RTAX, RTG4, SAM-ICE, Serial Quad I/O, simpleMAP, SimpliPHY, SmartBuffer, SmartHLS, SMART-I.S., storClad, SQI, SuperSwitcher, SuperSwitcher II, Switchtec, SynchroPHY, Total Endurance, Trusted Time, TSHARC, Turing, USBCheck, VariSense, VectorBlox, VeriPHY, ViewSpan, WiperLock, XpressConnect, and ZENA are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

The Adaptec logo, Frequency on Demand, Silicon Storage Technology, and Symmcom are registered trademarks of Microchip Technology Inc. in other countries.

GestIC is a registered trademark of Microchip Technology Germany II GmbH & Co. KG, a subsidiary of Microchip Technology Inc., in other countries.

All other trademarks mentioned herein are property of their respective companies.

© 2024, Microchip Technology Incorporated and its subsidiaries. All Rights Reserved.

ISBN: 978-1-6683-3847-6

Quality Management System

For information regarding Microchip's Quality Management Systems, please visit www.microchip.com/quality.

Worldwide Sales and Service

AMERICAS	ASIA/PACIFIC	ASIA/PACIFIC	EUROPE
Corporate Office 2355 West Chandler Blvd. Chandler, AZ 85224-6199 Tel: 480-792-7200 Fax: 480-792-7277 Technical Support: www.microchip.com/support Web Address: www.microchip.com	Australia - Sydney Tel: 61-2-9868-6733 China - Beijing Tel: 86-10-8569-7000 China - Chengdu Tel: 86-28-8665-5511 China - Chongqing Tel: 86-23-8980-9588 China - Dongguan Tel: 86-769-8702-9880 China - Guangzhou Tel: 86-20-8755-8029 China - Hangzhou Tel: 86-571-8792-8115 China - Hong Kong SAR Tel: 852-2943-5100 China - Nanjing Tel: 86-25-8473-2460 China - Qingdao Tel: 86-532-8502-7355 China - Shanghai Tel: 86-21-3326-8000 China - Shenyang Tel: 86-24-2334-2829 China - Shenzhen Tel: 86-755-8864-2200 China - Suzhou Tel: 86-186-6233-1526 China - Wuhan Tel: 86-27-5980-5300 China - Xian Tel: 86-29-8833-7252 China - Xiamen Tel: 86-592-2388138 China - Zhuhai Tel: 86-756-3210040	India - Bangalore Tel: 91-80-3090-4444 India - New Delhi Tel: 91-11-4160-8631 India - Pune Tel: 91-20-4121-0141 Japan - Osaka Tel: 81-6-6152-7160 Japan - Tokyo Tel: 81-3-6880-3770 Korea - Daegu Tel: 82-53-744-4301 Korea - Seoul Tel: 82-2-554-7200 Malaysia - Kuala Lumpur Tel: 60-3-7651-7906 Malaysia - Penang Tel: 60-4-227-8870 Philippines - Manila Tel: 63-2-634-9065 Singapore Tel: 65-6334-8870 Taiwan - Hsin Chu Tel: 886-3-577-8366 Taiwan - Kaohsiung Tel: 886-7-213-7830 Taiwan - Taipei Tel: 886-2-2508-8600 Thailand - Bangkok Tel: 66-2-694-1351 Vietnam - Ho Chi Minh Tel: 84-28-5448-2100	Austria - Wels Tel: 43-7242-2244-39 Fax: 43-7242-2244-393 Denmark - Copenhagen Tel: 45-4485-5910 Fax: 45-4485-2829 Finland - Espoo Tel: 358-9-4520-820 France - Paris Tel: 33-1-69-53-63-20 Fax: 33-1-69-30-90-79 Germany - Garching Tel: 49-8931-9700 Germany - Haan Tel: 49-2129-3766400 Germany - Heilbronn Tel: 49-7131-72400 Germany - Karlsruhe Tel: 49-721-625370 Germany - Munich Tel: 49-89-627-144-0 Fax: 49-89-627-144-44 Germany - Rosenheim Tel: 49-8031-354-560 Israel - Ra'anana Tel: 972-9-744-7705 Italy - Milan Tel: 39-0331-742611 Fax: 39-0331-466781 Italy - Padova Tel: 39-049-7625286 Netherlands - Drunen Tel: 31-416-690399 Fax: 31-416-690340 Norway - Trondheim Tel: 47-72884388 Poland - Warsaw Tel: 48-22-3325737 Romania - Bucharest Tel: 40-21-407-87-50 Spain - Madrid Tel: 34-91-708-08-90 Fax: 34-91-708-08-91 Sweden - Gothenberg Tel: 46-31-704-60-40 Sweden - Stockholm Tel: 46-8-5090-4654 UK - Wokingham Tel: 44-118-921-5800 Fax: 44-118-921-5820