



PRODUCT DATASHEET

Tina2 series

last update 26/7/2012

DETAILS

Product Number	CA12400_TINA2-D
Family	Tina2
Type	Assembly
Color	white
Diameter	16,1 mm
Height	10,47 mm
Style	round
Optic Material	PMMA
Holder Material	PC
Fastening	tape
Status	ready
ROHS Compliant	Yes
Date Updated	26/07/2012



OPTICAL PROPERTIES

LED	Viewing Angle	Light Beam	Efficiency	cd/lm	Connector
CL-L400	26 deg	Diffuser	93 %	3.200	-

D


C

B

A

4

4



Ø 16.1


3

3

Lens

Holder

Tape 0.4mm




10.47

2

2

Oval beam direction
(0-90 is turned 90 degree)



MATERIALS
 Lens: PMMA
 Holder: PC
 Tape: PU Foam

This drawing is our property.
 It can't be reproduced
 or communicated without
 our written agreement.



Ledil Oy
 Salorankatu 10
 FIN-24100 SALO
 Finland

DRAWING TITLE

Datasheet Tina2-CLL

DRAWN BY
ah

DATE
16.5.2012

CHECKED BY

DATE
16.5.2012

SIZE
A4

DRAWING NUMBER

REV
1

DESIGNED BY
ah

DATE
18.10.2011

SCALE

3:1

WEIGHT (g)

-

SHEET

1/1

D

A

1

1

NOTE: The typical divergence will be changed by different color, chip size and chip position tolerance. The typical total divergence is the full angle measured where the luminous intensity is half of the peak value.

GENERAL INFORMATION

- Product series especially designed & optimized for series of LEDs.
- Special care taken to make light distribution as uniform as possible.
- Fastening to heat sink with a PU foam adhesive tape of automotive grade. Please find fastening details by clicking link: http://www.ledil.com/datasheets/DataSheet_TAPE.pdf

NOTE 1: We advise customer to ensure the suitability and sufficiency of the bond in the end product. For example, mechanical stress, vibration and holes on the surface of the circuit board weaken the strength of the tape.

NOTE 2: Assembly to the surface must be made straight, so the tape bonds constant and balanced with fastening surface. Slanted assembly might cause unbalanced bond to the surface. All surfaces where tape is applied must be clean, dry and free from grease and dirt.

If cleaning of PCB surfaces is needed, please follow strictly the cleaning instructions of your LED manufacturer - this is important as cleaning shall under no circumstances damage LEDs or other electronics components on the PCB.

Further note that optical components shall not be cleaned with any chemicals - only micro fiber cloth may be used to remove fingerprints or other traces from handling.