

PRODUCT DATASHEET Strada-SQ series

LUXE

last update 28/9/2012



Ordering number C12410

Description C12410_STRADA-SQ-A-T

Family Strada-SQ FWHM Asym degrees

Type Lens Efficiency 93 % LED LUXEON M cd/lm -

Color Clear Gerber File Available

Diameter 25 + 25 mm
Height 9 mm
Style Square

tyle Square Positioning: External position element / Automatic assembling li

Optic Material PMMA Holder Material -

Fastening Screw, glue Status Ready

Ordering number CA12411

Description CA12411_STRADA-SQ-A-T

Strada-SQ **FWHM** Asym degrees Family Lens Efficiency 93 % Type LED LUXEON M cd/lm 0.410 Color Clear Gerber File Available

Diameter 25 + 25 mm
Height 9.15 mm
Style Square

Optic Material PMMA
Holder Material -

Fastening Screw, tape Status Ready Positioning: External position element / Automatic assembling li

October 9th 2012 14:57 Copyright Ledil Oy - Subject to change without prior notice - Page 1/3



PRODUCT DATASHEET Strada-SQ series last update 28/9/2012



NOTE: The typical divergence will be changed by different color, chip size and chip position tolerance. The typical total divergence is the full angle measured where the luminous intensity is half of the peak value.



PRODUCT DATASHEET Strada-SQ series



last update 28/9/2012

GENERAL INFORMATION

- Product series especially designed & optimized for LUXEON M series of LEDs.
- Special care taken to make light distribution as uniform as possible.
- Fastening to heat sink with a PU foam adhesive tape of automotive grade. Please find fastening details by clicking link: http://www.ledil.com/datasheets/DataSheet_TAPE.pdf
- Fastening to PCB with appropriate adhesive. By clicking link below you can find Ledil recommended glue options.

http://www.ledil.com/datasheets/DataSheet_GLUES.pdf

NOTE 1: We advise customer to ensure the suitability and sufficiency of the bond in the end product. For example, mechanical stress, vibration and holes on the surface of the circuit boar weaken the strength of the tape.

NOTE 2: Assembly to the surface must be made straight, so the tape bonds constant and balanced with fastening surface. Slanted assembly might cause unbalanced bond to the surface. All surfaces where tape is applied must be clean, dry and free from grease and dirt.


If cleaning of PCB surfaces is needed, please follow strictly the cleaning instructions of your LED manufacturer - this is important as cleaning shall under no circumstances damage LEDs or other electronics components on the PCB.

Further note that optical components shall not be cleaned with any chemicals - only micro fiber cloth may be used to remove fingerprints or other traces from handling.


NOTE 1: We advise customer to ensure the suitability and sufficiency of the bond in the end product. For example, mechanical stress, vibration and holes on the surface of the circuit boar weaken the strength of the glue.

NOTE 2: All surfaces where glue is applied must be clean, dry and free from grease and dirt. If cleaning of PCB surfaces is needed, please follow strictly the cleaning instructions of your LED manufacturer -this is important as cleaning shall under no circumstances damage LEDs or other electronics components on the PCB.

Further note that optical components shall not be cleaned with any chemicals - only micro fiber cloth may be used to remove fingerprints or other traces from handling.



Luminaire: Ledil Oy C12410_STRADA-SQ-A-T (Luxeon M) Efficiency=93% Lamps: 1 x Luxeon M 362Im @ 250mA



Luminaire: Ledil Oy C12411_STRADA-SQ-A-T (Luxeon M) Efficiency=93% Lamps: 1 x Luxeon M 362lm @ 250mA

