


DETAILS

Product Number	FA10337_NIS83-MX-SS
Family	Rose
Type	Assembly
Color	white
Diameter	21,6 + 21,6 mm
Height	13,5 mm
Style	square
Optic Material	PC
Holder Material	PC
Fastening	tape
Status	ready
ROHS Compliant	Yes
Date Updated	24/06/2014



OPTICAL PROPERTIES

LED	Viewing Angle	Light Beam	Effi- ciency	cd/lm	Connector
NS6x83	14 deg	Smooth spo...-		9.680	-
MX-6	16 deg	Smooth spo...88 %		6.460	-



<div>Tolerances if not otherwise shown According to DIN ISO 2768-1 Linear measures: Up to 30mm class M, otherwise class C. According to DIN ISO 2768-2 Form and position: class L</div>		<div><div>LEDiL</div><div>Ledil Oy Salorankatu 10 FIN 24240 SALO Finland</div></div>			
<div>THIRD ANGLE PROJECTION:<div></div></div>		<div>DRAWING TITLE</div> <div>Datasheet NIS83-MX</div>			
<div>This drawing is the property of LEDiL Oy. It may not be reproduced, copied or communicated without a written agreement with LEDiL Oy."</div>		<div>SIZE</div> <div>A4</div>	<div>PART NUMBER</div> <div>-</div>		
		<div>SCALE</div> <div>2:1</div>	<div>WEIGHT</div> <div>-</div>	<div>SHEET</div> <div>1 / 1</div>	

NOTE: The typical divergence will be changed by different color, chip size and chip position tolerance. The typical total divergence is the full angle measured where the luminous intensity is half of the peak value.

GENERAL INFORMATION

- Product series especially designed & optimized for series of LEDs.
- Special care taken to make light distribution as uniform as possible.
- Fastening to heat sink with a PU foam adhesive tape of automotive grade. Please find fastening details by clicking link: http://www.ledil.com/datasheets/DataSheet_TAPE.pdf

NOTE 1: We advise customer to ensure the suitability and sufficiency of the bond in the end product. For example, mechanical stress, vibration and holes on the surface of the circuit board weaken the strength of the tape.

NOTE 2: Assembly to the surface must be made straight, so the tape bonds constant and balanced with fastening surface. Slanted assembly might cause unbalanced bond to the surface. All surfaces where tape is applied must be clean, dry and free from grease and dirt.

If cleaning of PCB surfaces is needed, please follow strictly the cleaning instructions of your LED manufacturer - this is important as cleaning shall under no circumstances damage LEDs or other electronics components on the PCB.

Further note that optical components shall not be cleaned with any chemicals - only micro fiber cloth may be used to remove fingerprints or other traces from handling.