# **Voltage Controlled Oscillator**

**ROS-100+** 

#### **Linear Tuning** 50 to 100 MHz

#### **Features**

- octave band tuning
- low phase noise, -105 dBc/Hz at 10 kHz
  linear tuning, 3-5 MHz/V typ.
- aqueous washable

#### **Applications**

- · test instruments-signal generators
- receivers
- VHF



CASE STYLE: CK605 PRICE: \$12.95 ea. QTY (5-49)

+ RoHS compliant in accordance with EU Directive (2002/95/EC)

The +Suffix has been added in order to identify RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications.

#### **Electrical Specifications**

FREQUENCY (MHz)		POWER OUTPUT (dBm)	TUNING VOLTAGE (V)		PHASE NOISE (dBc/Hz) SSB at offset frequencies: Typ.			PULLING pk-pk @ 12 dBr (MHz)		TUNING SENSITIVITY (MHz/V)		ONICS Bc)	3 dB MODULATION BANDWIDTH (MHz)	OPER	C ATING VER	
Min.	Max.	Тур.	Min.	Max.	1 kHz	10 kHz	100 kHz	1 MHz	Тур.	Тур.	Тур.	Тур.	Max.	Тур.	Vcc (volts)	Current (mA) Max.
50	100	+8.3	0.5	17	-75	-105	-125	-145	0.6	0.3	3.0-5.0	-30	-20	0.1	12	20

#### **Pin Connections**


RF OUT	10
VCC	14
V-TUNE	2
GROUND	1 3 4 5 6 7 8 9 11 12 13 15 16

#### **Maximum Ratings**


Operating Temperature	-55°C to 85°C
Storage Temperature	-55°C to 100°C
Absolute Max. Supply Voltage (Vcc)	) +13V
Absolute Max. Tuning Voltage (Vtun	e) +18V

all specifications: 50 ohm system
Permanent damage may occur if any of these limits are exceeded.

#### **Outline Drawing**



#### Demo Board MCL P/N: TB-10 Suggested PCB Layout (PL-012)



NOTES: 1. TRACE WIDTH IS SHOWN FOR FR4 WITH DIELECTRIC THICKNESS .030" ± .002"; COPPER: 1/2 0Z. EACH SIDE. FOR OTHER MATERIALS TRACE WIDTH MAY NEED TO BE MODIFIED. 2. BOTTOM SIDE OF THE PCB IS CONTINUOUS GROUND PLANE.

DENOTES PCB COPPER LAYOUT WITH SMOBC (SOLDER MASK OVER BARE COPPER)

DENOTES COPPER LAND PATTERN FREE OF SOLDER MASK

### Outline Dimensions (inch mm)

.500 .180 .100 .080 .115 .060 .040 .540 .060 .100 .135 .135 .115 .140 .070 .150 .070 grams 12.70 12.70 4.57 2.54 2.03 2.92 1.52 1.02 13.72 1.52 2.54 3.43 3.43 2.92 3.56

Mini-Circuits


ISO 9001 ISO 14001 AS 9100 CERTIFIED

For detailed performance specs & shopping online see web site


P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 The Design Engineers Search Engine Provides ACTUAL Data Instantly at minic


REV D

## Performance Data & Curves




V	TUNING SENS.	FREG	QUENCY	(MHz)	POWER OUTPUT (dBm)			
TUNE	(MHz/V)	-55°C	+25°C	+85°C	-55°C	+25°C	+85°C	
1.0	5.6	48.6	46.7	44.9	9.3	9.3	9.2	
2.0	4.5	53.1	51.2	49.4	9.6	9.5	9.4	
3.0	4.1	57.2	55.3	53.3	9.6	9.6	9.5	
4.0	3.6	61.0	58.9	56.8	9.6	9.6	9.4	
5.0	3.6	64.8	62.5	60.4	9.5	9.5	9.3	
6.0 7.0 8.0 9.0	3.6 3.9 3.9 4.2 4.2	68.5 72.4 76.6 81.0 85.4	66.2 70.1 74.0 78.2 82.4	63.9 67.6 71.4 75.3 79.4	9.4 9.2 9.1 8.9 8.8	9.4 9.2 9.1 8.9 8.8	9.2 9.1 8.9 8.8 8.6	
11.0	4.3	89.8	86.7	83.5	8.6	8.6	8.4	
12.0	4.4	94.3	91.1	87.7	8.3	8.4	8.2	
13.0	4.4	98.9	95.5	91.9	8.1	8.1	8.0	
14.0	4.5	103.5	100.0	96.2	7.9	7.9	7.7	
15.0	4.5	108.1	104.4	100.5	7.6	7.7	7.5	
16.0	4.5	112.7	109.0	104.9	7.4	7.4	7.2	
17.0	4.4	117.2	113.4	109.2	7.1	7.2	7.0	





_ V	HA	FREQ. PUSHIN		
TUNE	F2	F3	F4	(MHz/V)
1.0	-38.9	-37.3	-48.7	0.3
2.0	-39.4	-38.1	-47.7	0.3
3.0	-36.8	-38.1	-47.0	0.3
4.0	-36.1	-37.9	-46.8	0.1
5.0	-36.7	-37.6	-46.8	0.1
6.0	-38.2	-37.2	-47.1	0.1
7.0	-40.6	-36.8	-47.3	0.2
8.0	-43.6	-36.6	-47.3	0.1
9.0	-46.3	-36.8	-47.0	0.3
10.0	-48.5	-36.9	-45.7	0.3
11.0	-50.3	-37.0	-44.1	0.3
12.0	-49.4	-37.3	-42.3	0.3
13.0	-46.7	-37.3	-40.6	0.3
14.0	-45.1	-37.3	-38.9	0.3
15.0	-43.9	-36.9	-37.3	0.4
16.0	-41.9	-36.2	-35.8	0.5
17.0	-39.2	-35.6	-34 7	0.6



For detailed performance specs & shopping online see web site