

N2POWER XL275 DC-DC SERIES

ULTRA SMALL, HIGH-EFFICIENCY POWER SUPPLIES

HIGHLIGHTS

- 275W DC-DC
- 3" X 5" Small Footprint
- Up to 91% Efficiency
- High Power Density: 12 W / cu in.
- All Outputs may be Paralleled
- Remote On / Off
- 5W 5V Standby Supply
- 36 76 VDC Input
- Active Current Sharing
- Built in OR-ing MOSFET for N, N+1
- PMBus[™] Interface for Digital Power Management (optional)
- RoHS Compliant
- Input to Output Isolation

POWER SUPPLY DESIGN LEADER

N2Power continues to lead the power density race with its small, high efficiency XL275 DC-DC power supplies. Our state of the art technology yields a very small footprint, reduces wasted power, and offers the highest power density in its class. This unique design means reduced energy costs, a greater return on your investment, higher reliability and longer product life.

ADVANCED DIGITAL CONTROLLER

The XL275 is the first power supply in this class to use a dedicated digital microcontroller to supervise the unit's operation. The microcontroller monitors the following parameters:


- DC input voltage
- Output voltage
- Output current
- Transformer temperature
- Ambient temperature
- Fan tachometer


The microcontroller enables the main output whenever all of the required startup conditions are met, and shuts it down upon command, loss of input power or whenever excessive loads or temperatures are sensed.



Typical Mechanical Drawing:

Inches (millimeters), connectors and pinouts may vary with model. Refer to XL275 Product Specification for complete information.





PMBus™ OPTION

An optional PMBusTM digital communications interface is also provided to allow up to four XL275 to communicate over the same bus using the PMBus protocol. This interface allows routine remote control of the main outputs and the 12V fans. It can also notify the host if a fan fails (lost tachometer pulses). The host can also query the microcontroller for its output voltage and current plus the ambient and transformer temperatures. Because it is programmable, the microcontroller code can be customized to meet unique OEM requirements.

Contact us regarding custom and modified standard supplies for unique applications.













QUALSTAR CORPORATION www.n2power.com Tel: 805-583-7744

NASDAQ: QBAK



N2POWER XL275 DC-DC SERIES

ULTRA SMALL, HIGH-EFFICIENCY POWER SUPPLIES

| MODEL | PART NUMBER | ОИТРИТ | VOLTAGE | REGULATION (%) | MAXIMUM CURRENT (A) | RIPPLE & NOISE (P-P) |
|-----------------------------|----------------------------|--------|---------|-------------------|------------------------|-------------------------|
| XL275-12DC XL275-12DC CS | 400084-03-4 400085-03-1 | V1 | 12 | ±3 | 22.9 | 100 mV |
| | | V2 | 12 | ±5 | 1.0 | 80 mV |
| | | V3 | 5sb | ±5 | 1.0 | 50 mV |
| XL275-24DC XL275-24DC CS | 400084-05-9 400085-05-6 | V1 | 24 | ±3 | 11.5 | 200 mV |
| | | V2 | 12 | ±5 | 1.0 | 80 mV |
| | | V3 | 5sb | ±5 | 1.0 | 50 mV |
| XL275-48DC XL275-48DC CS | 400084-06-7 400085-06-4 | V1 | 48 | ±3 | 5.7 | 200 mV |
| | | V2 | 12 | ±5 | 1.0 | 80 mV |
| | | V3 | 5sb | ±5 | 1.0 | 50 mV |
| XL275-54DC XL275-54DC CS | 400084-09-1 400085-09-8 | V1 | 54 | ±3 | 5.1 | 200 mV |
| | | V2 | 12 | ±5 | 1.0 | 80 mV |
| | | V3 | 5sb | ±5 | 1.0 | 50 mV |
| XL275-56DC XL275-56DC CS | 400084-10-9 400085-10-6 | V1 | 56 | ±3 | 4.9 | 200 mV |
| | | V2 | 12 | ±5 | 1.0 | 80 mV |
| | | V3 | 5sb | ±5 | 1.0 | 50 mV |

CS = Current Sharing

Compliance: 1

Downloaded from Arrow.com.

USA / Canada Safety: UL 60950-1:2007 (2nd Edition) / C22.2 No. 60950-1-07 UL 62368-1 (Second Edition)

Safety of Information Technology Equipment

FCC part 15, subpart B

2006/95/EC - "Low Voltage (Safety) Directive"

Demko: EN 60950-1:2006 (2nd Edition) + A11:2009 (2nd Edition) EN 62368-1:2014 / A11:2017

2004/108/EC "Electromagnetic Compatibility (EMC) Directive"

EN 61204-3 Class B

¹ See Product Specification for additional information

International

IEC 60950-1:2005 (2nd Edition)

IEC 62368-1:2014

Safety of Information Technology

Equipment

IEC 61204-3 Class B

Nominal Input Voltage: 36 - 76 VDC Input Current: 9.2 A @ 36 VDC

Input Protection: 10 A fuse

3000 V input to output Safety Isolation: 1500 V input to ground

OUTPUT SPECIFICATIONS

275W Total Power: Efficiency: Up to 91% † Minimum Load: No load †

Over / Under Shoot: Maximum 10% at turn-on

PROTECTION

Overvoltage Protection: V1 and V2 latch off Overpower Protection: Protected / Auto-recovery Auto recovery of all outputs Short Circuit Protection: protected against short circuit

Auto recovery protection

Thermal Shutdown: against over-temperature conditions

OPERATING SPECIFICATIONS

-25°C to +50°C Operating Temperature:

Temperature Derating: 2.5% / degree C 50°C to 70°C

Storage Temperature: -40°C to +85°C Forced Air Cooling: 10 CFM minimum

Convection Cooling: 150W

> 200,000 hours (calculated) MTBF:

SIGNALS

Remote Sense: V1 and Return

Active Current Sharing: V1 using OR-ing MOSFET V2 and V3 outputs may be Passive Redundancy:

wire OR-ed

Fan Output 1: V2 on a 2-pin keyed connector ON above 45°C ambient or Fan Output 2:

hot transformer (Optional) Reports fan speed

Fan Tachometer Input: via PMBus

Provides PMBus control /

Optional PC Data/Clock: status interface

High-true CMS logic and LED Power Good Output: drive outputs

LED drive on when V1 and V2

Standby Output: outputs disabled

Low-true input enables V1 and

V2 outputs†

Onboard LED DC On, Power Good Indicators:

Remote Enable Input:

For complete specifications on all models, please visit our website at: www.n2power.com

All information and specifications are based on our knowledge of the products at the time of printing. N2Power reserves the right to change specifications without notice.

Qualstar and the Qualstar logo are registered trademarks of Qualstar Corporation. N2Power and the N2Power logo are trademarks of Qualstar Corporation. All other trademarks are the property of their respective owners.













INPUT SPECIFICATIONS

[†] See Product Specification