



LCP1531

ASD (Application Specific Devices)

Programmable transient voltage suppressor for SLIC protection

Features

- Dual programmable transient suppressor
- Wide negative firing voltage range:
 $V_{MGL} = -150 \text{ V max.}$
- Low dynamic switching voltages:
 V_{FP} and V_{DGL}
- Low gate triggering current: $I_{GT} = 5 \text{ mA max}$
- Peak pulse current: $I_{PP} = 37.5 \text{ A (5/310 } \mu\text{s)}$
- Holding current: $I_H = 150 \text{ mA min}$
- Low space consuming package

Description


These devices have been especially designed to protect new high-voltage, as well as classical SLICs, against transient overvoltage.

Positive overvoltages are clamped by 2 diodes. Negative surges are suppressed by 2 thyristors, their breakdown voltage being referenced to $-V_{BAT}$ through the gate.

These components present a very low gate triggering current (I_{GT}) in order to reduce the current consumption on printed circuit board during the firing phase.

Benefits


TRISILs™ are not subject to ageing and provide a fail-safe mode in short circuit for better protection. They are used to help equipment to meet various standards such as YDT695, and ITU-T K20/21. TRISILs are UL94 V0 resin approved and are UL497B approved [file: E136224]).



Order code

Part Number	Marking
LCP1531RL	CP153

Figure 1. LCP1531 Functional Diagram



TM: TRISIL is a trademark of STMicroelectronics

1 Characteristics

Table 1. Compliance with the following Standards

Standard	Peak surge voltage (V)	Voltage waveform	Required peak current (A)	Current waveform	Minimum serial resistor to meet standard (Ω)
YDT695, ITU-T-K20/K21	1500	10/700 μ s	37.5	5/310 μ s	0
ITU-T-K20 (IEC 61000-4-2)	8000 15000	1-60 ns	ESD contact discharge ESD air discharge		0 0

Table 2. Thermal Resistance

Symbol	Parameter	Value	Unit
$R_{th(j-a)}$	Junction to ambient	120	$^{\circ}\text{C/W}$

Table 3. Electrical Characteristics ($T_{amb} = 25^{\circ}\text{C}$)

Symbol	Parameter	
I_{GT}	Gate triggering current	
I_H	Holding current	
I_{RM}	Reverse leakage current LINE / GND	
I_{RG}	Reverse leakage current GATE / LINE	
V_{RM}	Reverse voltage LINE / GND	
V_{GT}	Gate triggering voltage	
V_F	Forward drop voltage LINE / GND	
V_{FP}	Peak forward voltage LINE / GND	
V_{DGL}	Dynamic switching voltage GATE / LINE	
V_{RG}	Reverse voltage GATE / LINE	
C	Capacitance LINE / GND	

Table 4. Absolute ratings ($T_{amb} = 25^{\circ} \text{C}$, unless otherwise specified)

Symbol	Parameter		Value	Unit
I_{PP}	Peak pulse current	5/310 μs	37.5	A
I_{TSM}	Non-repetitive surge peak on-state current (50Hz sinusoidal)	$t = 20\text{ms}$ $t = 200\text{ms}$ $t = 1\text{s}$	16 9 6	A
I_{GSM}	Maximum gate current (50Hz sinusoidal)	$t = 10\text{ms}$	2	A
V_{MLG}	Maximum voltage LINE/GND		-150	V
V_{MGL}	Maximum voltage GATE/LINE		-150	V
T_{stg} T_j	Storage temperature range Maximum junction temperature		-55 to +150 150	$^{\circ} \text{C}$
T_L	Maximum lead temperature for soldering during 10 s.		260	$^{\circ} \text{C}$

Table 5. Repetitive peak pulse current


Symbol	Definition	Example	
t_r	Rise time (μs)	Pulse waveform 5/310 μs : $t_r = 5 \mu\text{s}$ $t_p = 310 \mu\text{s}$	
t_p	Pulse duration (μs)		

Table 6. Parameters related to the diode LINE / GND ($T_{amb} = 25^{\circ} \text{C}$)

Symbol	Test conditions		Max	Unit
V_F	$I_F = 5\text{A}$	$t = 500 \mu\text{s}$	3	V
$V_{FP}^{(1)}$	10/700 μs $V_{PP} = 1.5 \text{ kV}$	$R_S = 15 \Omega$	5	V

1. see test circuit for V_{FP} ; R_S is the protection resistor located on the line card.

Table 7. Parameters related to the protection Thyristors ($T_{amb} = 25^{\circ} \text{C}$)

Symbol	Test conditions	Min	Max	Unit
I_{GT}	$V_{GND} / \text{LINE} = -48 \text{ V}$	0.1	5	mA
I_H	$V_{GATE} = -48 \text{ V}^{(1)}$	150		mA
I_{RG}	$V_{RG} = -75 \text{ V}$		5	μA
V_{DGL}	$V_{GATE} = -48 \text{ V}^{(2)}$ 10/700 μs $V_{PP} = 1.5 \text{ kV}$ $R_S = 15 \Omega$ $I_{PP} = 27.5 \text{ A}$		7	V

1. see functional holding current (I_H) test circuit

2. see test circuit for V_{DGL} . The oscillations with a time duration lower than 50 ns are not taken into account.

Table 8. Parameters related to diode and protection Thyristors ($T_{amb} = 25^{\circ}C$, unless otherwise specified)

Symbol	Test conditions	Typ	Max	Unit
I_{RM}	$V_{GATE / LINE} = -1V$ $V_{RM} = -75V$ $T_j = 25^{\circ}C$		5	μA
C	$V_R = 50V$ bias, $V_{RMS} = 1V$, $F = 1MHz$ $V_R = 2V$ bias, $V_{RMS} = 1V$, $F = 1MHz$	15 35		pF

2 Technical information

Figure 2. Functional holding current (I_H) test circuit: GO-NO GO test




Figure 3. Test circuit for V_{FP} and V_{DGL} parameters





Figure 4. LCP1531 concept behavior

Figure 4. shows the classical protection circuit using the LCP1531 crowbar concept. This topology has been developed to protect the new high voltage SLICs. It allows to program the negative firing threshold while the positive clamping value is fixed at GND.

When a negative surge occurs on one wire (L1 for example) a current I_G flows through the base of the transistor T1 and then injects a current in the gate of the thyristor Th1. Th1 fires and all the surge current flows through the ground. After the surge when the current flowing through Th1 becomes less negative than the holding current I_H , then Th1 switches off.

When a positive surge occurs on one wire (L1 for example) the diode D1 conducts and the surge current flows through the ground.


Figure 5. Example of PCB layout based on LCP1531 protection

Figure 5. shows the classical PCB layout used to optimize line protection.

The capacitor C is used to speed up the crowbar structure firing during the fast surge edges.

This allows to minimize the dynamical breakover voltage at the SLIC Tip and Ring inputs during fast strikes. Note that this capacitor is generally present around the SLIC - Vbat pin.

So to be efficient it has to be as close as possible from the LCP1531 Gate pin and from the reference ground track (or plan) (see *Figure 5.*). The optimized value for C is 220 nF.

The series resistors Rs1 and Rs2 designed in *Figure 4.* represent the fuse resistors or the PTC which are mandatory to withstand the power contact or the power induction tests imposed by the various country standards. Taking into account this fact the actual lightning surge current flowing through the LCP1531 is equal to:

$$I_{\text{surge}} = V_{\text{surge}} / (R_g + R_s)$$

With:

V_{surge} = peak surge voltage imposed by the standard.

R_g = series resistor of the surge generator

R_s = series resistor of the line card (e.g. PTC)

The LCP1531 is particularly optimized for the new telecom applications such as the fiber in the loop, the WLL, the remote central office. In this case, the operating voltages are smaller than in the classical system. This makes the high voltage SLICs particularly suitable.

The schematics of [Figure 6](#) gives the most frequent topology used for these applications.

Figure 6. Protection of high voltage SLIC




Figure 7. Surge peak current versus overload duration





Figure 8. Relative variation of holding current versus junction temperature




3 Package information

- Epoxy meets UL94, V0

Table 9. SO-8 dimensions

Ref	Dimensions					
	Millimeters			Inches		
	Min	Typ	Max	Min	Typ	Max
A			1.75			0.069
A1	0.1		0.25	0.004		0.010
A2	1.25			0.049		
b	0.28		0.48	0.011		0.019
C	0.17		0.23	0.007		0.009
D	4.80	4.90	5.00	0.189	0.193	0.197
E	5.80	6.00	6.20	0.228	0.236	0.244
E1	3.80	3.90	4.00	0.150	0.154	0.157
e		1.27			0.050	
h	0.25		0.50	0.010		0.020
L	0.40		1.27	0.016		0.050
L1		1.04			0.041	
k°	0		8	0		8
ccc			0.10			0.004

Figure 9. SO-8 footprint (dimensions in mm)



In order to meet environmental requirements, ST offers these devices in ECOPACK® packages. These packages have a lead-free second level interconnect. The category of second level interconnect is marked on the package and on the inner box label, in compliance with JEDEC Standard JESD97. The maximum ratings related to soldering conditions are also marked on the inner box label. ECOPACK is an ST trademark. ECOPACK specifications are available at: www.st.com.

4 Ordering information

Part Number	Marking	Package	Weight	Base qty	Delivery mode
LCP1531RL	CP153	SO-8	0.08 g	2500	Tape and reel

5 Revision history

Date	Revision	Description of Changes
31-Mar-2007	1	First issue.

Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY AN AUTHORIZED ST REPRESENTATIVE, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2007 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com