



Tripp Lite
1111 West 35th Street
Chicago, IL 60609 USA
Telephone: +(773) 869 1234
E-mail: saleshelp@tripplite.com

Model #: PV3000GFCI

PowerVerter Plus Inverter w/ GFCI Outlets - Industrial-Strength Power for Heavy-Duty Applications

Highlights



- 12V DC input; 120V AC output; 4 outlets **GFCI** protected (NEMA 5-15R)
- 3000 watts continuous output; 6000 watts peak output (instantaneous)
- Quiet electricity for TVs, DVD players, microwaves, power tools, coffee makers and game systems
- Includes "Battery Saver" low voltage alarm/shutdown
- Remote Control LED/Switch Module and Cable included
- Meets OSHA requirements

Description

Utilize your vehicle's battery to efficiently power office equipment on the road or power tools at a work site. Continuously supplies up to 3000 watts of 120V AC power to 4 AC GFCI protected outlets from any 12V battery or automotive DC source. Includes a PV remote and 25 feet of cable.

Super-compact, lightweight metal case design is among the smallest, most rugged inverters available at this power level. Conforms to OSHA 1926.404 (b) (1) (ii)

Applications

AC Power to meet all your equipment needs; including air compressors, water pumps, heater, fans, power tools, lights, splicing systems, portable power tool chargers as well as TVs, DVD players, microwaves, refrigerators, coffeemakers and game systems under 3000 watts.

Package Includes

- PV3000GFCI Inverter
- Remote control LED/switch module (APSRM4)
- 25-ft. remote cable
- Warranty information
- Instruction manual

Features

- Converts DC power into 3000 watts of continuous 120V AC power
- 15- and 20-amp outlets provide 120V AC power

- Includes "Battery Saver" low voltage alarm/shutdown
- Heavy-duty DC input terminals assure solid connection to battery. Dual connections provide high wattage to support heavy equipment loads.
- Operating mode switch controls inverter operation.
- Remote control jack provides optional remote monitoring and control (when used with FREE, included LED/switch module)
- Remote Control LED/Switch Module controls and monitors your inverter from virtually anywhere within your vehicle with use of included extra-long cable. Allows multiple mounting options, including behind or below a dashboard or compartment. Features daisy-chain capability
- Battery charge level LEDs indicate the approximate charge level (high/medium/low) of connected batteries
- Connected load level LEDs indicate the approximate wattage load level (high/medium/low) of connected equipment
- Sturdy extruded aluminum case stands up to the toughest work environments
- Battery conservation charge dial conserves battery power by setting the low-load level at which the inverter automatically shuts off
- Cooling fans provide cooler operation, lengthening inverter service life
- Circuit breakers guard the inverter against potentially damaging equipment overload
- Mounting flanges provide safe, fixed installation
- Grooved cooling surface provides additional surface area for more efficient cooling
- Grounding lug connects to vehicle ground

Specifications

SYSTEM OVERVIEW	
Voltage compatibility	Compatible with 12VDC automotive or battery power sources
OUTPUT	
Frequency compatibility	60 Hz
Output watts	3000W (continuous)/6000W (peak)
Continuous output capacity (watts)	3000
Peak output capacity (watts)	6000
Output nominal voltage	120V
Output voltage regulation	Maintains PWM sine wave output voltage of 115 VAC (+/- 8 VAC)
Output frequency regulation	60 Hz (+/- 3 Hz)
Overload protection	Automatic overload protection shuts down inverter system in the event of overloads. Output is protected by 2 built-in 20A circuit breakers (each controlling power to 2 outlets). Inverter and electrical system are further protected via set of 6 40A automotive input fuses.
Outlet quantity / type	4 AC outlets GFCI Protected (NEMA 5-15R)
INPUT	
Recommended Electrical Service	Requires 12VDC input source capable of delivering 286A for the required duration (when used at full capacity). For automotive applications, professional hardwire installation with 500A battery system fusing is recommended.
Maximum input amps	Full continuous load - 286A at 12VDC, No load - 1.5A at 12VDC, Shutdown / load sense mode - less than 100 microamps
Input cord length (ft.)	User supplies cabling. Minimum gauges for full load operation: 0 (10 ft max), 00 or 2/0 (13 ft max), Twin 00 using 4 conductors (26 ft)
BATTERY	
DC system voltage	12V
LEDS ALARMS & SWITCHES	

Alarms	Dual function alarm indicates overload conditions or low DC input voltage of 10.5V or less.
Switches	3 position rocker switch enables on/off power control, plus remote setting which enables inverter to be remotely powered on or off when used in conjunction with included APSRM4 module.
PHYSICAL	
Shipping weight (lbs)	13.7
Shipping weight (kg)	6.2
Cooling method	fan
Shipping Dimensions (HWD/in)	4.3 x 12.5 x 14.8
Shipping Dimensions (HWD/cm)	10.4 x 28.2 x 35.6
Unit weight (lbs)	12.2
Unit weight (kg)	5.5
Material of construction	Aluminum / sheet metal
Style	Heavy-duty
Form factors supported	Mounting slots enable permanent placement of inverter on any horizontal surface (see manual for additional mounting information)
ENVIRONMENTAL	
Relative Humidity	0-95% non-condensing
Operating Temperature	32-104 Fahrenheit / 0-40 Celcius
SPECIAL FEATURES	
Appearance	Attractive, rugged, metallic gray color inverter system
Remote control capability	Yes
TVSS grounding	Grounding lug grounds the inverter to vehicle or earth ground - user supplies cabling
WARRANTY	
Standard warranty period	1 year (Outside the U.S. and Canada, call for warranty information)

More information, including related products, owner's manuals, and additional technical specifications, can be found online at www.tripplite.com/en/products/model.cfm?txtModelID=4201.