

40 Pin Female IDE to Serial ATA (SATA) Drive Adapter Converter

MODEL NUMBER: **P936-000**



Highlights

- Convert existing IDE Drives to a SATA Controller
- Serial ATA (SATA) Data & Power Cable Included

System Requirements

- Supports any operating system when a PC with available IDE hard disk and SATA controller are used

Package Includes

- Serial ATA to IDE Converter x 1
- Serial ATA Cable x 1
- Power supply cable x 1
- User's Manual x 1

Description

Tripp Lite's P936-000, Serial ATA (SATA) to IDE converter, allows a standard parallel ATA hard disk drive, CD-ROM, CD-RW, DVD ROM, DVD + RW, etc, to be used with Serial ATA Controller cards or motherboards with Serial ATA ports, and meets the specification of Serial ATA 1.0 interface.

Simply plug the 40-pin side of the adapter into the IDE drive 40-pin connector, and attach power and SATA cables to the appropriate connections...no software to load.

Features

- Easily connect IDE/ATA Drives to a SATA Controller
- Compliance with Serial ATA Gen 1.0.
- Master/slave device emulation support.
- Supports PIO mode 0~4.
- Supports Ultra DMA mode 0~7.
- Supports UDMA data transfer rates of up to 150MBps
- Supports ATAPI Packet command set.
- Supports 48-bit LBA addressing.
- Supports additional ATA command for serial ATA SCR access.
- Serial ATA power save mode supported
- Serial ATA BIST operation.
- Supports hot-plugging

Specifications

UPC ASSIGNMENT

Unit Carton UPC#

037332152053



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

CONNECTIONS	
Connector A	 40 POS. SOCKET (FEMALE)
Connector B	 4 PIN (INTERNAL)
Connector C	 7 PIN SATA STRAIGHT (MALE)
WARRANTY	
Product Warranty Period (Worldwide)	Lifetime limited warranty

© 2014 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.