
AVR514: Migration from ATmega325 to ATmega325P

Features

- General Porting Considerations
- Register and bit names
- Low-frequency Crystal / Timer/Counter Oscillator

1 Introduction

This application note summarizes the relevant differences when migrating from ATmega325 to ATmega325P. For detailed information on the devices please see the respective datasheets.

The ATmega325P is designed to be pin and functionality compatible with ATmega325, but because of improvements mentioned in this application note there may be a need for minor modifications in the application when migrating from ATmega325 to ATmega325P.



8-bit **AVR**[®]
Microcontrollers

Application Note

Rev. 8063A-AVR-03/07





2 General Porting Considerations

To make the porting process as easy as possible, we recommend to always refer to registers and bit positions using their defined names, as absolute addresses and values may change from device to device. When porting a design it is then often just necessary to include the correct definition file. Some examples are shown below.

```
PORTE |= (1<<PORTE5);          // Set pin 5 on port E high
DDR  &= ~(1<<PORTE5);          // Set pin 5 on port E as input
// Configure USI
USICR = (1<<USISIE)|(0<<USIOIE)|(1<<USIWM1)|(0<<USIWM0)|
        (1<<USICS1)|(0<<USICS0)|(0<<USICLK)|(0<<USITC);
```

To avoid conflicts with added features and register functionality, never access registers that are marked as reserved. Reserved bits should always be written to zero if accessed. This ensures forward compatibility, and added features will stay in their default states when unused.

3 Register and bit names

Between ATmega325 and ATmega325P some register bits has been added, but none of the existing bits has been removed, nor moved to different locations.

4 Low-frequency Crystal / Timer/Counter Oscillator

The low-frequency crystal oscillator of the ATmega325P is different from the one in ATmega325. It is optimized for very low power consumption and thus the crystal driver strength is reduced compared to the ATmega325. This means that when selecting a crystal, its load capacitance and Equivalent Series Resistance (ESR) must be taken into consideration. Both values are specified in the crystal vendor. Table 4-1 shows the ESR recommendations for ATmega325P. The internal capacitance of ATmega325P oscillator is typically 6 pF, but the tracks to the crystal will add some additional capacitance.

Table 4-1. ESR recommendations for 32.768 kHz crystals for ATmega325P

Crystal CL [pF]	Max ESR [kΩ] ¹
6.5	75
9	65
12.5	30

Note: 1. The values stated are for an oscillator allowance safety margin of 5. Since the oscillator's transconductance is temperature compensated one can use a safety margin of 4, thus giving a max ESR of 90, 80 and 40 kΩ respectively.

For examples of crystals that comply with the requirements see Appendix A.

The startup times are also increased as shown in Table 4-2.

Table 4-2. Startup times with 32.768 kHz crystals for ATmega325P.

Crystal CL [pF]	Startup time ⁽²⁾ [ms] Atmega325	Startup time ⁽²⁾ [ms] Atmega325P
6.5	-	600
9	300	700
12.5	400	1700

Note: 2. Crystals usually need ~3000 ms before they are completely stable with any oscillator design. The time stated is before the crystal is running with a sufficient amplitude and frequency stability.

5 Appendix A

Table 5-1 is a selection of crystals that meet the ESR requirements of the ATmega325P. The crystals are listed based on datasheet information and are not tested with the actual device. Any other crystal that complies with the ESR requirements can also be used. Availability and RoHS compliance has not been investigated.

Table 5-1. Examples of crystals compliant with ATmega325P low-frequency Crystal Oscillator.

Vendor	Type	Mounting (SMD/HOLE)	Frequency Tolerance [±ppm]	Load Capacitance [pF]	Equivalent Series Resistance (ESR) [kΩ]
C-MAC	WATCH CRYSTALS	HOLE	20	6	50
C-MAC	85SMX	SMD	20	6	55
C-MAC	90SMX	SMD	20	6	60
ECLIPTEK®	E4WC	HOLE	20	6	50
ENDRICH	90SMX	SMD	5	6	50
EPSON®	C-001R	HOLE	20	6 -> 12.5 (specify)	35
EPSON	C-002RX	HOLE	20	6 -> 10 (specify)	50
EPSON	C-004R	HOLE	20	6 -> 10 (specify)	50
EPSON	C-005R	HOLE	20	6 -> 10 (specify)	50
EPSON	MC-30A	SMD	20	6 -> 10 (specify)	50
EPSON	MC-306	SMD	20	6 -> 10 (specify)	50
EPSON	MC-405	SMD	20	6 -> 10 (specify)	50
EPSON	MC-406	SMD	20	6 -> 10 (specify)	50
GOLLEDGE	GWX	HOLE	5	6, 8 or 12.5	35
GOLLEDGE	GSWX-26	SMD	10	6, 8 or 12.5	35
GOLLEDGE	GDX1	HOLE	10	6	42
GOLLEDGE	GSX-200	SMD	5	6	50
IQD	WATCH CRYSTALS	HOLE	20	6	50
IQD	90SMX	HOLE	10	6	60
IQD	91SMX	HOLE	10	6	60





Vendor	Type	Mounting (SMD/HOLE)	Frequency Tolerance [±ppm]	Load Capacitance [pF]	Equivalent Series Resistance (ESR) [kΩ]
MICROCRYSTAL	MS3V-T1R	HOLE	20	7 or 9	65
MICROCRYSTAL	MS2V-T1R	HOLE	20	7 or 9	65
MICROCRYSTAL	CC4V-T1A	SMD	30	9	65
MICROCRYSTAL	CC1V-T1A	SMD	30	9	60
MICROCRYSTAL	CC7V-T1A	SMD	30	9	70
MMD	WC26	HOLE	8	8	35
MMD	WC38	HOLE	8	8	35
MMD	WC155	HOLE	8	8	40
MMD	WCSMC	SMD	20	6	50
OSCILENT	SERIES 111	HOLE	10	6 or 12.5	30
OSCILENT	SERIES 112	HOLE	10	6 or 12.5	40
OSCILENT	SERIES 113	HOLE	10	8	40
OSCILENT	SERIES 223	SMD	20	6	50
RALTRON	SERIES R38	HOLE	5	6 or 12.5	35
RALTRON	SERIES R26	HOLE	5	6 or 12.5	35
RALTRON	SERIES R145	HOLE	5	8	40
RALTRON	SERIES RSE A, B, C, D	SMD	20	6	50
SBTRON	SBX-13	SMD	20	6	50
SBTRON	SBX-20	SMD	20	6	50
SBTRON	SBX-21	SMD	20	6	50
SBTRON	SBX-24	SMD	20	6	50
SBTRON	SBX-23	SMD	20	6	50
SBTRON	SBX-22	SMD	20	6	50
SBTRON	SBX-14	HOLE	20	6	50
SUNTSU	SCT1	HOLE	20	6, 8, 10 or 12.5	40
SUNTSU	SCT2	HOLE	20	6, 8, 10	50
SUNTSU	SCT3	HOLE	20	6, 8, 10	50
SUNTSU	SCP1	SMD	20	6	50
SUNTSU	SCT2G	SMD	20	6 or 10	50



Headquarters

Atmel Corporation

2325 Orchard Parkway
San Jose, CA 95131, USA
Tel: 1(408) 441-0311
Fax: 1(408) 487-2600

International

Atmel Asia

Room 1219
Chinachem Golden Plaza
77 Mody Road Tsimshatsui
East Kowloon
Hong Kong
Tel: (852) 2721-9778
Fax: (852) 2722-1369

Atmel Europe

Le Krebs
8, Rue Jean-Pierre Timbaud
BP 309
78054 Saint-Quentin-en-Yvelines
Cedex
France
Tel: (33) 1-30-60-70-00
Fax: (33) 1-30-60-71-11

Atmel Japan

9F, Tonetsu Shinkawa Bldg.
1-24-8 Shinkawa
Chuo-ku, Tokyo 104-0033
Japan
Tel: (81) 3-3523-3551
Fax: (81) 3-3523-7581

Operations

Memory

2325 Orchard Parkway
San Jose, CA 95131, USA
Tel: 1(408) 441-0311
Fax: 1(408) 436-4314

Microcontrollers

2325 Orchard Parkway
San Jose, CA 95131, USA
Tel: 1(408) 441-0311
Fax: 1(408) 436-4314

La Chantrerie
BP 70602
44306 Nantes Cedex 3
France
Tel: (33) 2-40-18-18-18
Fax: (33) 2-40-18-19-60

ASIC/ASSP/Smart Cards

Zone Industrielle
13106 Rousset Cedex
France
Tel: (33) 4-42-53-60-00
Fax: (33) 4-42-53-60-01

1150 East Cheyenne Mtn. Blvd.
Colorado Springs, CO 80906, USA
Tel: 1(719) 576-3300
Fax: 1(719) 540-1759

Scottish Enterprise Technology Park
Maxwell Building
East Kilbride G75 0QR
Scotland
Tel: (44) 1355-803-000
Fax: (44) 1355-242-743

RF/Automotive

Theresienstrasse 2
Postfach 3535
74025 Heilbronn
Germany
Tel: (49) 71-31-67-0
Fax: (49) 71-31-67-2340

1150 East Cheyenne Mtn. Blvd.
Colorado Springs, CO 80906, USA
Tel: 1(719) 576-3300
Fax: 1(719) 540-1759

Biometrics

Avenue de Rochepleine
BP 123
38521 Saint-Egreve Cedex
France
Tel: (33) 4-76-58-47-50
Fax: (33) 4-76-58-47-60

Literature Requests

www.atmel.com/literature

Disclaimer: The information in this document is provided in connection with Atmel products. No license, express or implied, by estoppel or otherwise, to any intellectual property right is granted by this document or in connection with the sale of Atmel products. **EXCEPT AS SET FORTH IN ATMEL'S TERMS AND CONDITIONS OF SALE LOCATED ON ATMEL'S WEB SITE, ATMEL ASSUMES NO LIABILITY WHATSOEVER AND DISCLAIMS ANY EXPRESS, IMPLIED OR STATUTORY WARRANTY RELATING TO ITS PRODUCTS INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT. IN NO EVENT SHALL ATMEL BE LIABLE FOR ANY DIRECT, INDIRECT, CONSEQUENTIAL, PUNITIVE, SPECIAL OR INCIDENTAL DAMAGES (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR LOSS OF PROFITS, BUSINESS INTERRUPTION, OR LOSS OF INFORMATION) ARISING OUT OF THE USE OR INABILITY TO USE THIS DOCUMENT, EVEN IF ATMEL HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.** Atmel makes no representations or warranties with respect to the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and product descriptions at any time without notice. Atmel does not make any commitment to update the information contained herein. Unless specifically provided otherwise, Atmel products are not suitable for, and shall not be used in, automotive applications. Atmel's products are not intended, authorized, or warranted for use as components in applications intended to support or sustain life.

© 2007 Atmel Corporation. All rights reserved. Atmel®, logo and combinations thereof, Everywhere You Are® and AVR®, are the registered trademarks of Atmel Corporation or its subsidiaries. Other terms and product names may be trademarks of others.